

- 10. Quick Loop** – Spider IV features built in looping functionality. Press **Quick Loop** to arm looper:

**To record a loop**

- A) To begin recording, press **TAP** to set the loop start
- B) To start playback, press **TAP** to set the loop end
- C) Press **TAP** to stop playback

**To Overdub**

- A) When loop is in playback press, hold and release **TAP** to set Overdub start point
- B) Press **TAP** to end overdub and start playback
- C) Press **TAP** to stop playback


**To Clear your Loop**

- A) Stop loop playback
- B) Press and hold **TAP** for 3 seconds
- C) Display will confirm your loop is cleared.

To Exit Loop Control Mode, press **Quick Loop** button again.

- 11. Presets & Editing** – The display shows various “pages” as you work the controls.

**Preset Mode**



Left/right selects between preset types (Bands, Style, User)  
 Up/down selects next/previous folder of this preset type

**PRESETS**



Knob selects next/previous preset from current folder

**Edit Mode**



Left/right selects between blocks of parameters  
 Up/down selects next/previous parameter in this block of parameters

**PRESETS**



Knob adjusts selected parameter

**Momentary Model Select**



**PRESETS**



Knob selects alternate Models, while display is shown.

## REAR PANEL CONTROLS & CONNECTIONS

- 12. Power Connector and Fuse** – The included power cable connects here. See the rear panel markings for fuse information.
- 13. Phones/Direct Outs** – Connect a pair of stereo headphones here. When you do so, the speakers are muted. This jack also doubles as a Direct Output. Use a stereo 1/4” TRS cable to connect to a mixer or recording device.
- 14. CD/MP3 Inputs** – Plug in any audio source to jam with your favorite music or drum machine. Use the device’s output control to adjust the volume. Start with the volume on your device at it’s lowest setting and bring it up to volume you desire.
- 15. FBV** – Connect a Line 6 FBV Express MkII™ for channel switching, tap tempo, wah/volume control and tuner capabilities. Connect a Line 6 FBV Shortboard MkII™ controller for channel switching, effects on/off control, wah/volume pedals, access to more channel memories, tuner, and tap tempo. (Also compatible with original FBV series controllers)
- 16. Speaker Outs** – Available on the 150 and HD150 models only. Provides an 8 ohm load at each jack, wired in parallel, to give a 4 ohm load if used simultaneously. Use a speaker cable, DO NOT use a guitar cable.

**Get Advanced Guide and more online [www.line6.com/manuals](http://www.line6.com/manuals)**

Get up to speed on your Spider IV deep editing features with our Advanced User Guide available online. Discover how to customize Amp and Effect Model defaults, deep edit effects parameters, enabling boosts, advanced Loop functions and much more. While you’re online be sure to register your Spider IV or simply fill out and mail us your included registration card. Registering gets you all set up for warranty service should you have an issue with your Spider IV, and also qualifies you for contests, special offers and more.