

Accutronics (and other) Reverb Tank Codes

n

Specification	Code	Description
Reverb Type (Pretty much swappable within same tank length)	1	Short (9 1/4") 2 spring unit
	3	Short (9 1/4") 3 spring unit
	4	Long (16 3/4") 2 spring unit
	8	Short (9 1/4") 3 spring unit
	9	Long (16 3/4") 3 spring unit
Input Impedance	A	8 - 10 Ohms (.8 - 1.3 Ohms DC)
	B	150 - 190 Ohms (25 - 26 Ohms DC)
	C	200 - 240 Ohms (27 - 30 Ohms DC)
	D	250 - 310 Ohms (33 - 36 Ohms DC)
	E	600 - 800 Ohms (58 - 76 Ohms DC)
	F	1,475 - 1925 Ohms (200 - 800 Ohms DC)
Output Impedance	A	500 - 600 Ohms (40-42 Ohms DC)
	B	2250 - 2575 Ohms (200 - 214 Ohms DC)
	C	10,000 - 12,000 Ohms (800 Ohms DC)
Decay Time (Not critical)	1	Short (1.2 to 2.0 sec.)
	2	Medium (1.75 to 3.0 sec.)
	3	Long (2.75 to 4.0 sec.)
Connectors (A floating ground is sometimes necessary (JCM2000!))	A	Input and Output Grounded
	B	Input Grounded, Output Insulated
	C	Input Insulated, Output Grounded
	D	Input and Output Insulated
	E	No Outer Channel
Locking Devices	1	No Lock
Mounting Plane (This does not seem to matter)	A	Horizontal, Open Side Up
	B	Horizontal, Open Side Down
	C	Vertical, Connectors Up
	D	Vertical, Connectors Down
	E	On End, Input Up
	F	On End, Output Up

Fender Vintage & RI:
4**AB3C1B**, 9**AB2C1B**,
9**AB3C1B**

Fender Blues Jr.: 8**EB2C1B**

Fender Hot Rod, Blues DeVille:
4**EB3C1B** (Fender #0050394000)

Fender Red Knob Twin:
9**FB2A1C** (common works OK)

Marshall 900: 8**DB2C1D** (some used 8**DB2C1B**).

Marshall 2000: 4**BB3C1x**
(Feedback? try a 4**DB2C1D**)

Mesa F100: 9**BB2A1B**

Mesa MK..., Lonestars, TV, HB,
RK: 9**AB2A1B**

Peavey KB/A 300: 8**EB2C1B**

Peavey Nashville: 4**EB2C1B**

Roland JC120: 8**AB2D1A** (some older units use 8**DB2C1B**).

SWR California Blonde (and II):
1**BB2D1B** or 8**BB2D1B**

Vox AC30 Chinese: 4**EB3C1B**,
4**EB2C1B**, 8**EB2C1B**, 9**EB2C1B**
Ruby Tubes RRV53**EB1C1B**,
Belton 3**EB3C1B** (Junk!),

Tank sources:
NewSensor, TubesAndMore,
AmpRepairParts (Revisit tanks)

Updated 2014-10-26