

		Ersatzteilliste - Bill of Materials		
	112863	SUB 800A 230V		
Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung	Menge Qty	Description
		Zubehör		Accessories & packing material
	361276	BEDIENUNGSANL. SUB 800A	1	owner's manual
	339967	POLYBEUTEL 200X280X0,15	1	poly bag
	359309	KABEL-NETZ EU 16A/250V	1	power cord 230V
	361313	KRT. SUB 800A 667X432X605	1	carton SUB800A
	345156	SCHUTZHÜLLE 1160X1200X0,08	1	poly bag
		Mechanische Teile		Cabinet material
L0001	361142	LA DL 15 Y	1	woofer DL 15Y
L0002	354281	FILTERSP. 6.80MH/ 0.58OHM	1	inductor 6.80mh
	344514	GRIFF 209,6X173,7	2	handle EV #20265
	343091	BEZ.SCHILD GRIFF DYNACORD	2	name plate handle
	360529	DICHTG-SEGM GRIFF 344514	2	gasket for handle
	361570	SCHUTZG. SUB800A	1	front grille SUB800A
	360728	ZUSCHN. 560X388 PPI 20	1	foam, grille
	357796	BEZ.SCHILD D LOGO SW-SI	1	DYNACORD logo
	359570	GEWINDEFL. M20 24116-000-55	1	stand mount threaded
	358009	DICHTG-SEGM HOCHSTÄNDER	1	gasket for stand mount
	302735	DICHTG-SEGM LA 15"	4	gasket 15"
	345694	FUSS-GUMMI 3133 M	4	rubber foot
	306554	ROLLE-LENK 3360 PVO 080 P62	4	castor
	361210	GEH.SUB 800 A	1	enclosure SUB800A
	361306	SUB 800A 230V	1	amp assy SUB800A 230V
B0001	359273	BUCHSE-KALTGERÄTE-POWER CON	1	connector mains
S0001	359274	SCHALTER-NETZ M.SIGNALLAMPE	1	switch, mains
	353905	DK 11 GR/GR/RT B 6FL	1	knob rotary gr/rd
	330605	SICHER-HALTER	1	fuseholder
	330632	SICHER-HALTER-KAPPE	1	cap of fuse holder
	302587	SICHER T 3.150 A/250V	1	fuse 3.15A slow blow
	352260	KABEL-KONFEKT 12POL 0.130M	1	ribbon cable assy 12-way
	361136	FRONTBL-BED ACTIVE-SUB	1	front panel
	359251	RKT SUB 800A 230V/240V	1	power transformer 230/240V
	348309	WI-SO PTC K155 100GRAD	1	resistor ptc
	348341	FEDERLEISTE 3POL CE100-	1	connector female 3-pole
	813498	PCB SUB 800 A N 4	1	pcb assy 81349
CN001	348802	MESSERLST. 12POL	1	connector male 12-pin
C0001	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C0002	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C0003	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C0004	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF
C0005	358639	KO-EL 220.000MF 16V	1	cap electrolytic 220uF/16V
C0006	358639	KO-EL 220.000MF 16V	1	cap electrolytic 220uF/16V
C0007	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0008	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0009	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0010	345461	KO-KER 680.0PF 100V 10%	1	cap ceramic 680pF

	112863	SUB 800A 230V				
Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung			Menge Qty	Description
C0011	345461	KO-KER	680.0PF	100V 10%	1	cap ceramic 680pF
C0012	345461	KO-KER	680.0PF	100V 10%	1	cap ceramic 680pF
C0013	345461	KO-KER	680.0PF	100V 10%	1	cap ceramic 680pF
C0014	329021	KO-KER	0.10MF	100V 20%	1	cap ceramic 100nF
C0015	301530	KO-KER	100.0PF	500V 10%	1	cap ceramic 100pF
C0016	301530	KO-KER	100.0PF	500V 10%	1	cap ceramic 100pF
C0017	329021	KO-KER	0.10MF	100V 20%	1	cap ceramic 100nF
C0018	340524	KO-EL	100.000MF	16V	1	cap electrolytic 100uF/16V
C0021	301558	KO-KER	33.0PF	100V 2%	1	cap ceramic 33pF
C0022	301558	KO-KER	33.0PF	100V 2%	1	cap ceramic 33pF
C0023	340524	KO-EL	100.000MF	16V	1	cap electrolytic 100uF/16V
C0024	301530	KO-KER	100.0PF	500V 10%	1	cap ceramic 100pF
C0025	301530	KO-KER	100.0PF	500V 10%	1	cap ceramic 100pF
C0026	345461	KO-KER	680.0PF	100V 10%	1	cap ceramic 680pF
C0027	358639	KO-EL	220.000MF	16V	1	cap electrolytic 220uF/16V
C0028	358639	KO-EL	220.000MF	16V	1	cap electrolytic 220uF/16V
C0029	345461	KO-KER	680.0PF	100V 10%	1	cap ceramic 680pF
C0030	340523	KO-EL	22.000MF	16V	1	cap electrolytic 22uF/16V
C0031	340522	KO-EL	10.000MF	35V	1	cap electrolytic 10uF/35V
C0032	329021	KO-KER	0.10MF	100V 20%	1	cap ceramic 100nF
C0033	345461	KO-KER	680.0PF	100V 10%	1	cap ceramic 680pF
C0034	345461	KO-KER	680.0PF	100V 10%	1	cap ceramic 680pF
C0035	345461	KO-KER	680.0PF	100V 10%	1	cap ceramic 680pF
C0036	345461	KO-KER	680.0PF	100V 10%	1	cap ceramic 680pF
C0037	348814	KO-KER	220.0PF	K 500V 2%	1	cap ceramic 220pF
C0038	340524	KO-EL	100.000MF	16V	1	cap electrolytic 100uF/16V
C0039	343532	KO-EL	100.000MF	25V	1	cap electrolytic 100uF/25V
C0040	329021	KO-KER	0.10MF	100V 20%	1	cap ceramic 100nF
C0041	329021	KO-KER	0.10MF	100V 20%	1	cap ceramic 100nF
C0042	340524	KO-EL	100.000MF	16V	1	cap electrolytic 100uF/16V
C0043	343532	KO-EL	100.000MF	25V	1	cap electrolytic 100uF/25V
C0044	342923	KO-FOL	0.220MF	63V 5%	1	cap mylar 220nF
C0045	342923	KO-FOL	0.220MF	63V 5%	1	cap mylar 220nF
C0046	340524	KO-EL	100.000MF	16V	1	cap electrolytic 100uF/16V
C0047	335787	KO-KER	15.0PF	100V 2%	1	cap ceramic 15pF
C0048	340524	KO-EL	100.000MF	16V	1	cap electrolytic 100uF/16V
C0049	342923	KO-FOL	0.220MF	63V 5%	1	cap mylar 220nF
C0050	342923	KO-FOL	0.220MF	63V 5%	1	cap mylar 220nF
D0001	352093	LED GN	3MM LG	3369-EH	1	LED green 3mm
D0002	340243	LED RT	3MM LS	3369-EH	1	LED red 3mm
D0003	357450	LED GE	3MM LY	3369-EH	1	LED yellow 3mm
D0004	340243	LED RT	3MM LS	3369-EH	1	LED red 3mm
D0005	301254	DIODE 1N 4148	AXIAL		1	diode 1N 4148
D0006	304360	DIODE 1N 4007	GEGURTET		1	diode 1N 4002
D0007	304360	DIODE 1N 4007	GEGURTET		1	diode 1N 4002
E0001	356761	RELAIS M4-12H			1	relay 12V / dpdt
E0002	356761	RELAIS M4-12H			1	relay 12V / dpdt
H0001	343457	DICKS-NETZW.	8PIN	2%	1	res.network 8x10k Ohm
H0002	343457	DICKS-NETZW.	8PIN	2%	1	res.network 8x10k Ohm
H0003	343457	DICKS-NETZW.	8PIN	2%	1	res.network 8x10k Ohm
H0004	343457	DICKS-NETZW.	8PIN	2%	1	res.network 8x10k Ohm
H0005	343457	DICKS-NETZW.	8PIN	2%	1	res.network 8x10k Ohm

	112863	SUB 800A 230V		
Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung	Menge Qty	Description
H0006	343457	DICKS-NETZW. 8PIN 2%	1	res.network 8x10k Ohm
I0001	357454	IC NJM 5532 L SINGLE IN	1	IC NJM 5532
I0003	357454	IC NJM 5532 L SINGLE IN	1	IC NJM 5532
I0004	357454	IC NJM 5532 L SINGLE IN	1	IC NJM 5532
I0005	354931	IC NJM 072 BL SINGLE IN	1	IC NJM 072
I0006	358898	IC MC 33178 2FACH OP	1	IC MC 33178
I0007	354931	IC NJM 072 BL SINGLE IN	1	IC NJM 072
I0008	354931	IC NJM 072 BL SINGLE IN	1	IC NJM 072
JS001	359276	BUCHSE-COMBO XLR/KLINKE	1	connector XLR&phone jack
JS002	357371	STECKER-FL. XLR 3POL PRINTB	1	connector XLR male 3-pin
JS003	357371	STECKER-FL. XLR 3POL PRINTB	1	connector XLR male 3-pin
JS004	359276	BUCHSE-COMBO XLR/KLINKE	1	connector XLR&phone jack
JS005	357371	STECKER-FL. XLR 3POL PRINTB	1	connector XLR male 3-pin
JS006	357371	STECKER-FL. XLR 3POL PRINTB	1	connector XLR male 3-pin
Q0001	301184	TRANS BC 550 C	1	transistor BC 550 B
Q0002	301184	TRANS BC 550 C	1	transistor BC 550 B
VR001	359303	P-DREH 50KOHM LOG-	1	pot 50k Ohm neg log
	842118	PCB SUB 800 A	1	pcb assy 842118
CN-L1	330269	FL.STECKER 6.3/0.8	1	connector 6.3mm faston
CN-L2	330269	FL.STECKER 6.3/0.8	1	connector 6.3mm faston
CNAC1	343516	FL.STECKER 4.8/0.5	1	connector 4.8mm faston
CNAC2	343516	FL.STECKER 4.8/0.5	1	connector 4.8mm faston
CNAC3	330269	FL.STECKER 6.3/0.8	1	connector 6.3mm faston
CNAC4	330269	FL.STECKER 6.3/0.8	1	connector 6.3mm faston
CNAC5	330269	FL.STECKER 6.3/0.8	1	connector 6.3mm faston
CNAC6	330269	FL.STECKER 6.3/0.8	1	connector 6.3mm faston
CNE +	330269	FL.STECKER 6.3/0.8	1	connector 6.3mm faston
CNE -	330269	FL.STECKER 6.3/0.8	1	connector 6.3mm faston
CNGND	343516	FL.STECKER 4.8/0.5	1	connector 4.8mm faston
CNGN2	330269	FL.STECKER 6.3/0.8	1	connector 6.3mm faston
CNGN3	330269	FL.STECKER 6.3/0.8	1	connector 6.3mm faston
CNS01	354306	STIFTLEISTE 16POL	0,5	connector male 16-pin
CNS02	358756	STIFTLEISTE 5POL STL11S-1	1	connector male 5-pin
CNS04	337395	STIFTLEISTE 6POL	1	connector male 6-pin
CN001	348802	MESSERLST. 12POL	1	connector male 12-pin
CN002	348334	STIFTLEISTE 3POL MLSS	1	connector male 3-pin
C0001	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0002	359281	KO-KER 68.0PF 500V 2%	1	cap ceramic 68pF
C0003	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C0004	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C0005	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0006	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0007	307445	KO-EL 10.000MF 35V	1	cap electrolytic 10uF/35V
C0008	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0009	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C0010	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C0011	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0012	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0013	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0014	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0015	342923	KO-FOL 0.220MF 63V 5%	1	cap mylar 220nF

	112863	SUB 800A 230V		
Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung	Menge Qty	Description
C0016	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0017	340522	KO-EL 10.000MF 35V	1	cap electrolytic 10uF/35V
C0018	340988	KO-FOL 0.470MF 63V 5%	1	cap mylar 470nF
C0019	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0020	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0021	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0022	301519	KO-KER 10.0PF 500V 10%	1	cap ceramic 10pF
C0023	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0024	335787	KO-KER 15.0PF 100V 2%	1	cap ceramic 15pF
C0025	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0026	301519	KO-KER 10.0PF 500V 10%	1	cap ceramic 10pF
C0027	346975	KO-FOL 3300.000PF 100V 5%	1	cap mylar 3.3nF
C0028	340521	KO-EL 2.200MF 50V	1	cap electrolytic 2.2uF/50V
C0030	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0031	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0032	335787	KO-KER 15.0PF 100V 2%	1	cap ceramic 15pF
C0033	340523	KO-EL 22.000MF 16V	1	cap electrolytic 22uF/16V
C0034	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0035	356605	KO-FOL 0.100MF 250V 5%	1	cap mylar 100nF
C0036	301474	KO-EL 22.000MF 16V BIP	1	cap bip electr. 22uF/16V
C0037	301530	KO-KER 100.0PF 500V 10%	1	cap ceramic 100pF
C0038	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0039	342923	KO-FOL 0.220MF 63V 5%	1	cap mylar 220nF
C0040	342923	KO-FOL 0.220MF 63V 5%	1	cap mylar 220nF
C0041	332962	KO-EL 470.000MF 25V	1	cap electrolytic 470uF/25V
C0042	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0043	304986	KO-EL 2.200MF 50V	1	cap electrolytic 2.2uF/50V
C0044	337237	KO-FOL 0.047MF 100V 5%	1	cap mylar 47nF
C0045	340988	KO-FOL 0.470MF 63V 5%	1	cap mylar 470nF
C0046	342936	KO-FOL 0.150MF 63V 5%	1	cap mylar 150nF
C0047	341276	KO-FOL 0.012MF 100V 5%	1	cap mylar 12nF
C0048	344109	KO-FOL 0.056MF 63V 5%	1	cap mylar 56nF
C0049	344105	KO-FOL 0.027MF 100V 5%	1	cap mylar 27nF
C0050	332962	KO-EL 470.000MF 25V	1	cap electrolytic 470uF/25V
C0051	301524	KO-KER 47.0PF 500V 10%	1	cap ceramic 47pF
C0052	359282	KO-FOL 2700.000PF 250V 5%	1	cap mylar 2.7nF
C0053	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0054	301524	KO-KER 47.0PF 500V 10%	1	cap ceramic 47pF
C0055	301524	KO-KER 47.0PF 500V 10%	1	cap ceramic 47pF
C0056	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0057	359281	KO-KER 68.0PF 500V 2%	1	cap ceramic 68pF
C0058	359282	KO-FOL 2700.000PF 250V 5%	1	cap mylar 2.7nF
C0059	343533	KO-EL 220.000MF 25V	1	cap electrolytic 220uF/25V
C0060	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0061	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0062	356661	KO-EL 2200.000MF 35V	1	cap electrolytic 2200uF/35V
C0063	356661	KO-EL 2200.000MF 35V	1	cap electrolytic 2200uF/35V
C0064	341714	KO-SO 0.100MF 275V K 20%	1	safety cap 100nF/275V
C0065	341714	KO-SO 0.100MF 275V K 20%	1	safety cap 100nF/275V
C0066	359275	KO-EL 10000.00MF 63V 20%	1	cap electr. 10000uF/63V
C0067	359275	KO-EL 10000.00MF 63V 20%	1	cap electr. 10000uF/63V
C0068	359275	KO-EL 10000.00MF 63V 20%	1	cap electr. 10000uF/63V

	112863	SUB 800A 230V		
Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung	Menge Qty	Description
C0069	359275	KO-EL 10000.00MF 63V 20%	1	cap electr. 10000uF/63V
C0070	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0071	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0072	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0073	301527	KO-KER 68.0PF K 500V 10%	1	cap ceramic 68pF
C0074	301530	KO-KER 100.0PF 500V 10%	1	cap ceramic 100pF
C0075	307445	KO-EL 10.000MF 35V	1	cap electrolytic 10uF/35V
C0076	301527	KO-KER 68.0PF K 500V 10%	1	cap ceramic 68pF
C0077	343533	KO-EL 220.000MF 25V	1	cap electrolytic 220uF/25V
C0080	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0081	340524	KO-EL 100.000MF 16V	1	cap electrolytic 100uF/16V
C0082	356605	KO-FOL 0.100MF 250V 5%	1	cap mylar 100nF
D0001	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0002	304360	DIODE 1N 4007 GEGURTET	1	diode 1N 4002
D0003	304360	DIODE 1N 4007 GEGURTET	1	diode 1N 4002
D0004	304360	DIODE 1N 4007 GEGURTET	1	diode 1N 4002
D0005	304360	DIODE 1N 4007 GEGURTET	1	diode 1N 4002
D0006	304360	DIODE 1N 4007 GEGURTET	1	diode 1N 4002
D0007	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0008	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0009	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0010	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0011	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0012	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0013	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0014	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0015	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0016	309450	DIODZ BZX 55C 15V 0.50W	1	diode zener 15V
D0017	329511	DIODZ BZX 55C 2V4 0.50W	1	diode zener 2V4
D0018	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0019	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0020	304360	DIODE 1N 4007 GEGURTET	1	diode 1N 4002
D0021	309450	DIODZ BZX 55C 15V 0.50W	1	diode zener 15V
D0022	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0023	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0024	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0025	304360	DIODE 1N 4007 GEGURTET	1	diode 1N 4002
D0026	304360	DIODE 1N 4007 GEGURTET	1	diode 1N 4002
D0027	341613	DIODZ BZX 55C 51V 0.50W	1	diode zener 51V 0,5watt
D0028	301310	DIODZ BZX 55C 20V 0.50W	1	diode zener 20V 0,5watt
D0029	301297	DIODE BAT 85 SCHOTTKY	1	diode BAT 85
D0030	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0031	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0032	307916	DIODZ BZX 55C 7V5 0.50W	1	diode zener 7V5
D0033	307916	DIODZ BZX 55C 7V5 0.50W	1	diode zener 7V5
D0034	359280	DIODE MUR 1520	1	diode MUR 1520
D0035	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0036	359280	DIODE MUR 1520	1	diode MUR 1520
D0037	333733	DIODZ BZX 85C 12V 1.30W	1	diode zener 12V
D0038	305738	DIODZ BZX 55C 12V 0.50W	1	diode zener 12V
D0039	305738	DIODZ BZX 55C 12V 0.50W	1	diode zener 12V
D0040	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148

	112863	SUB 800A 230V		
Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung	Menge Qty	Description
D0041	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0042	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0043	304360	DIODE 1N 4007 GEGURTET	1	diode 1N 4002
D0044	304360	DIODE 1N 4007 GEGURTET	1	diode 1N 4002
D0045	304360	DIODE 1N 4007 GEGURTET	1	diode 1N 4002
D0046	304360	DIODE 1N 4007 GEGURTET	1	diode 1N 4002
D0047	304992	DIODZ BZX 55C 6V8 0.50W	1	diode zener 6V8
D0048	304992	DIODZ BZX 55C 6V8 0.50W	1	diode zener 6V8
D0049	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
E0001	354859	RELAIS 793-P-1C-S 24VDC	1	relay 24V
E0002	356594	RELAIS 793-P-1A-S-TV10	1	relay 24V / spst
00005	359277	GLRI GBU 12K 800V	1	rectifier GBU 12K
00005	359277	GLRI GBU 12K 800V	1	rectifier GBU 12K
H0001	343457	DICKS-NETZW. 8PIN 2%	1	res.network 8x10k Ohm
H0002	343457	DICKS-NETZW. 8PIN 2%	1	res.network 8x10k Ohm
I0001	354199	IC SPNG.REG. LM 317 T	1	IC LM 317 voltage regulator
I0002	354929	IC SPNG.REG. LM 337 T	1	IC LM 337 voltage regulator
I0003	327197	IC NE 5532 P 2FACH OP	1	IC NE 5532 N
I0004	332985	IC TL 074 CN	1	IC TL 074 CN
I0005	327197	IC NE 5532 P 2FACH OP	1	IC NE 5532 N
I0006	307421	IC CA 3080 E OTA	1	IC CA 3080 E
I0007	354919	IC OP 97 FP	1	IC OP 97
I0008	331340	IC TL 072 CP 2FACH OP	1	IC TL 072 CP
I0009	330767	IC LM 311 P 1-F.VCOMP	1	IC LM 311
I0010	330767	IC LM 311 P 1-F.VCOMP	1	IC LM 311
L0001	348592	FILTERSP. 2.50UH/0.004OHM	1	coil 2.5uH
PARKI	330269	FL.STECKER 6.3/0.8	1	connector 6.3mm faston
00005	359283	TRANS 2SC 5200	1	transistor 2SC 5200
00005	359283	TRANS 2SC 5200	1	transistor 2SC 5200
00005	359283	TRANS 2SC 5200	1	transistor 2SC 5200
Q0004	348409	TRANS 2SC 4793	1	transistor 2SC 4793
Q0005	307150	TRANS BC 337-25 TO 92	1	transistor BC 337-25
Q0006	306928	TRANS BC 560 C	1	transistor BC 560 C
Q0007	306928	TRANS BC 560 C	1	transistor BC 560 C
Q0008	306928	TRANS BC 560 C	1	transistor BC 560 C
Q0009	306928	TRANS BC 560 C	1	transistor BC 560 C
Q0010	348408	TRANS 2SA 1837	1	transistor 2SA 1837
Q0011	307150	TRANS BC 337-25 TO 92	1	transistor BC 337-25
Q0012	348421	TRANS 2N 3906	1	transistor 2N 3906
Q0013	335763	TRANS 2N 3904	1	transistor 2N 3904
Q0014	307150	TRANS BC 337-25 TO 92	1	transistor BC 337-25
Q0015	348422	TRANS MPSA 42	1	transistor MPSA 42
Q0016	348409	TRANS 2SC 4793	1	transistor 2SC 4793
Q0017	348422	TRANS MPSA 42	1	transistor MPSA 42
Q0018	335763	TRANS 2N 3904	1	transistor 2N 3904
Q0019	335763	TRANS 2N 3904	1	transistor 2N 3904
Q0020	348421	TRANS 2N 3906	1	transistor 2N 3906
Q0021	330264	TRANS J 111	1	transistor J 111 A
Q0022	335763	TRANS 2N 3904	1	transistor 2N 3904
Q0023	335763	TRANS 2N 3904	1	transistor 2N 3904
Q0024	348421	TRANS 2N 3906	1	transistor 2N 3906
Q0025	348421	TRANS 2N 3906	1	transistor 2N 3906

	112863	SUB 800A 230V		
Pos. Nr.	Best. Nr.		Menge	
Ref. No.	Part No.	Bezeichnung	Qty	Description
Q0026	348421	TRANS 2N 3906	1	transistor 2N 3906
Q0027	348421	TRANS 2N 3906	1	transistor 2N 3906
Q0028	348421	TRANS 2N 3906	1	transistor 2N 3906
Q0029	335763	TRANS 2N 3904	1	transistor 2N 3904
Q0030	348423	TRANS MPSA 92	1	transistor MPSA 92
Q0031	348423	TRANS MPSA 92	1	transistor MPSA 92
Q0032	348408	TRANS 2SA 1837	1	transistor 2SA 1837
Q0033	335763	TRANS 2N 3904	1	transistor 2N 3904
Q0034	348421	TRANS 2N 3906	1	transistor 2N 3906
Q0035	348422	TRANS MPSA 42	1	transistor MPSA 42
Q0036	348409	TRANS 2SC 4793	1	transistor 2SC 4793
Q0037	348423	TRANS MPSA 92	1	transistor MPSA 92
Q0038	348422	TRANS MPSA 42	1	transistor MPSA 42
00005	359285	TRANS 2SA 1943	1	transistor 2SA 1943
00005	359285	TRANS 2SA 1943	1	transistor 2SA 1943
00005	359285	TRANS 2SA 1943	1	transistor 2SA 1943
Q0042	307430	TRANS BC 327-25 TO 92	1	transistor BC 327-25
Q0043	307430	TRANS BC 327-25 TO 92	1	transistor BC 327-25
Q0044	348423	TRANS MPSA 92	1	transistor MPSA 92
Q0045	307911	TRANS BF 393	1	transistor BF 391
Q0046	307911	TRANS BF 393	1	transistor BF 391
Q0047	307912	TRANS BF 493 S TO 92	1	trans. BF 491
Q0048	307912	TRANS BF 493 S TO 92	1	trans. BF 491
Q0049	335763	TRANS 2N 3904	1	transistor 2N 3904
Q0050	348421	TRANS 2N 3906	1	transistor 2N 3906
Q0051	335763	TRANS 2N 3904	1	transistor 2N 3904
Q0052	348421	TRANS 2N 3906	1	transistor 2N 3906
Q0053	359279	TRANS IRFZ 44 R N-CHAN	1	transistor IRFZ 44 R
Q0054	306928	TRANS BC 560 C	1	transistor BC 560 C
Q0055	359279	TRANS IRFZ 44 R N-CHAN	1	transistor IRFZ 44 R
R0030	340299	WI-SI 2.20 OHM 0.30W 5%	1	safety resistor 2.20 Ohm
R0045	340299	WI-SI 2.20 OHM 0.30W 5%	1	safety resistor 2.20 Ohm
R0106	348590	WI-DR 8.20 OHM 4.00W 5%	1	resistor 8.20 Ohm 4watt
R0107	341713	WI-DR 4.70 OHM 4.00W 5%	1	resistor 4.70 Ohm 4watt
R0110	348456	WI-DR 2X 0.22 OHM 5.00W 5%	1	resistor 2x0.22 Ohm 5watt
R0114	348456	WI-DR 2X 0.22 OHM 5.00W 5%	1	resistor 2x0.22 Ohm 5watt
R0117	348456	WI-DR 2X 0.22 OHM 5.00W 5%	1	resistor 2x0.22 Ohm 5watt
00010	358977	WI-SO NTC 12.00 KOHM	1	resistor ntc
R0174	348593	WI-SO NTC 2.20 KOHM	1	safety component NTC
R0175	348593	WI-SO NTC 2.20 KOHM	1	safety component NTC
R0214	332306	WI-SCH 3.30 KOHM 2.00W 5%	1	resistor 3.3k Ohm 2watt
R0216	332306	WI-SCH 3.30 KOHM 2.00W 5%	1	resistor 3.3k Ohm 2watt
R0221	348550	WI-SO NTC 10.00 OHM K	1	resistor ntc 10 Ohm
S0001	327947	SCHALTELEMENT C42315-A1347-	0,125	switch element on/off
VR001	348674	WI-TRI 250.00 OHM LIN	1	pot trim 250 Ohm lin
VR002	348486	WI-TRI 47.00 KOHM LIN	1	pot trim 47k Ohm lin