

WORKINGMAN'S 15

200 watt, 1x15 combo amplifier with tweeter. Perfect for small to medium size gigs. Lightweight!

Speaker Complement:

- (1) Custom Designed 15" SWR driver
- (1) Custom Designed Piezo tweeter

Power Output: 160 Watts RMS, 200 Watts RMS @ 4 Ohms
(with 8 ohm extension speaker)

Impedance: 8 Ohms (internal)

Dimensions: 20.75" W x 27.625" H x 16.25" D

Weight: 61 lbs.

FRONT PANEL FEATURES

BALANCED DIRECT RECORD OUT

The Balanced XLR output is a true balanced output. No front panel controls affect its signal. The tone and output level are controlled only by the instrument plugged into one of the input jacks. To use this feature, run an XLR (Cannon) cable from the Balanced D.I. to the input of a tape machine, mixing console, etc. This output is also suitable for sending a signal to a house mixer in live situations.

Wiring for the XLR connector is as follows: Pin 1 = ground, Pin 2 = +, Pin 3 = -. (American standard)

TO TUNER

The To Tuner send jack allows the user to connect their instrument tuner to the Workingman's 15 without having to unplug and go back and forth from amp to tuner to amp. Like the Balanced D.I. output, this feature is isolated from the rest of the circuitry and no other controls other than your instrument have an affect on it. Being on a sidechain (isolated) also avoids loading down of the instrument which can cause a loss in dynamic range.

