

		Ersatzteilliste - Bill of Materials		
	112619	SP 7 SYSTEM-AMP		
Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung	Menge Qty	Description
		Zubehör		Accessories & packing material
	349832	R-HAL.LI.L24/1600 RACKHALTE	1	rack ear left
	349833	R-HAL.RE.L24/1600 RACKHALTE	1	rack ear right
	353470	BEDIENUNGSANL. SP 7	1	owner's manual SP7
	335589	FUSS-GUMMI SJ 5009 SW	4	rubber foot
	343846	AUFKLEBER UL-WARNH. DECKEL	1	sticker UL
	353475	KRT. SP 5 605X570X314	1	carton outer
	353476	KRT. IN SP 5 485X460X199	1	carton inner
	303715	STYROPOR-ECK 150X150X150X50	4	styrofoam #2
	348018	SCHUTZFOLIE 1200X800X0,05	2	poly bag
	327495	STYROPOR-ECK 150X150X100X50	4	styrofoam #1
	349988	FALTEINLAGE 750X280	1	carton filler #1
	353477	FALTEINLAGE 776X405	2	carton filler #2
		Mechanische Teile		Cabinet material
B0010	341343	BUCHSE-SPEAKON-VIERECK 4POL	4	speaker socket 4-pole
CN010	303581	FL.STECKVERTEILER A 6.3-2.5	4	connector faston 6.3
C0010	333014	KO-SO 0.100MF 275V L 20%	2	safety cap 100nF/275V
G0010	343270	GLRI GBPC 3504	2	rectifier GBPC-P 3504
S0010	346720	SCHALTER-NETZ ESB-99888V	1	power switch
	347348	DK 22 SW/GA C 6FL	2	rotary knob black
	341382	KNOPF-TASTE 20X8 SW 3.3	1	push button black
	361137	DK 16 KOMPL.	1	knob rotary s/a
	347347	DK 16 SW/SI C 6FL	1	knob rotary
	353478	DK 16 SW/SI A1 6FL	1	knob rotary
	349725	KABEL-NETZ BEARB.AUS 348800	1	power cord Europe
	348801	STECKER-NETZ-SCHUKO 3POL	1	mains plug
	353268	KABEL-KONFEKT 8POL 0.420M	2	ribbon cable assy 8-way
	353031	KABEL-KONFEKT 20POL 0.080M	1	ribbon cable assy 20-way
	353474	KABEL-KONFEKT 4POL 0.220M	1	ribbon cable assy 4-way
	351237	KABEL-KONFEKT 6POL 0.150M	2	ribbon cable assy 6-way
	353192	GRIF 153 MM ANTHR. 4HE	2	handle 153mm
	348415	LÜFTER TYP FBA08A24H DC	4	fan dc 24V
	353371	FB.SP 7 SYST-AMP BED	1	front panel SP 7
	353242	BLAUF.XA2600/PM2600	1	front grille
	353373	RW.OT.SP 7 SYST-AMP BED	1	rear panel top
	353196	RW.UT.XA2600/SP3/5/7 BEM	1	rear panel bottom
	353308	DEC.XA2600/PM2600 BEM	1	top cover
	351876	RKT XA2600/PM2600 230V	1	mains transformer 230V LO
	348341	FEDERLEISTE 3POL CE100-	1	connector female 3-pole
	348391	WI-SO PTC BEARB. AUS	1	resistor ptc
	348309	WI-SO PTC K155 100GRAD	1	resistor ptc
	348341	FEDERLEISTE 3POL CE100-	1	connector female 3-pole
	351877	RKT XA2600/PM2600 230V	1	mains transformer 230V HI
	348341	FEDERLEISTE 3POL CE100-	1	connector female 3-pole
	348805	WI-SO PTC K155 100GRAD	1	safety component PTC
	348341	FEDERLEISTE 3POL CE100-	1	connector female 3-pole

	112619	SP 7 SYSTEM-AMP		
Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung	Menge Qty	Description
	841668	PCB+A#XA2600/SP3/5/7	2	PCB assy 84166
CNOTA	330269	FL.STECKER 6.3/0.8	1	connector 6.3mm faston
CNOTB	330269	FL.STECKER 6.3/0.8	1	connector 6.3mm faston
CNSER	306446	FEDERLEISTE 2.5MM O 9POL	1	connector female 9-pole
CN002	344862	MESSERLST. 8POL	1	connector male 8-pin
C0001	351994	KO-KER 120.0PF 500V 2%	1	cap ceramic 120pF
C0002	351994	KO-KER 120.0PF 500V 2%	1	cap ceramic 120pF
C0003	301458	KO-EL 2.200MF 63V	1	cap electrolytic 2.2uF/63V
C0101	351994	KO-KER 120.0PF 500V 2%	1	cap ceramic 120pF
C0102	351994	KO-KER 120.0PF 500V 2%	1	cap ceramic 120pF
C0103	301458	KO-EL 2.200MF 63V	1	cap electrolytic 2.2uF/63V
D0001	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0002	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0003	307916	DIODZ BZX 55C 7V5 0.50W	1	diode zener 7V5
D0004	307916	DIODZ BZX 55C 7V5 0.50W	1	diode zener 7V5
D0005	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0006	328769	DIODE MR 752 BEARB.AUS	1	diode MR 752
D0007	328769	DIODE MR 752 BEARB.AUS	1	diode MR 752
D0008	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0101	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0102	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0103	307916	DIODZ BZX 55C 7V5 0.50W	1	diode zener 7V5
D0104	307916	DIODZ BZX 55C 7V5 0.50W	1	diode zener 7V5
D0105	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0106	328769	DIODE MR 752 BEARB.AUS	1	diode MR 752
D0107	328769	DIODE MR 752 BEARB.AUS	1	diode MR 752
D0108	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
Q0001	348409	TRANS 2SC 4793	1	transistor 2SC 4793
Q0002	351981	TRANS MJL 3281 A	1	transistor MJL 3281 A
Q0003	331657	TRANS MJ 15022	1	transistor MJ 15022
Q0004	331657	TRANS MJ 15022	1	transistor MJ 15022
Q0005	331657	TRANS MJ 15022	1	transistor MJ 15022
Q0006	331657	TRANS MJ 15022	1	transistor MJ 15022
Q0007	331657	TRANS MJ 15022	1	transistor MJ 15022
Q0008	331657	TRANS MJ 15022	1	transistor MJ 15022
Q0009	348408	TRANS 2SA 1837	1	transistor 2SA 1837
Q0010	351982	TRANS MJL 1302 A	1	transistor MJL 1302 A
Q0011	331658	TRANS MJ 15023	1	transistor MJ 15023
Q0012	331658	TRANS MJ 15023	1	transistor MJ 15023
Q0013	331658	TRANS MJ 15023	1	transistor MJ 15023
Q0014	331658	TRANS MJ 15023	1	transistor MJ 15023
Q0015	331658	TRANS MJ 15023	1	transistor MJ 15023
Q0016	331658	TRANS MJ 15023	1	transistor MJ 15023
Q0017	348409	TRANS 2SC 4793	1	transistor 2SC 4793
Q0018	348421	TRANS 2N 3906	1	transistor 2N 3906
Q0019	335763	TRANS 2N 3904	1	transistor 2N 3904
Q0020	348421	TRANS 2N 3906	1	transistor 2N 3906
Q0021	335763	TRANS 2N 3904	1	transistor 2N 3904
Q0022	348422	TRANS MPSA 42	1	transistor MPSA 42
Q0023	348423	TRANS MPSA 92	1	transistor MPSA 92

	112619	SP 7 SYSTEM-AMP		
Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung	Menge Qty	Description
Q0024	348423	TRANS MPSA 92	1	transistor MPSA 92
Q0025	348423	TRANS MPSA 92	1	transistor MPSA 92
Q0026	348423	TRANS MPSA 92	1	transistor MPSA 92
Q0027	348422	TRANS MPSA 42	1	transistor MPSA 42
Q0028	307911	TRANS BF 393	1	transistor BF 391
Q0029	307911	TRANS BF 393	1	transistor BF 391
Q0101	348409	TRANS 2SC 4793	1	transistor 2SC 4793
Q0102	351981	TRANS MJL 3281 A	1	transistor MJL 3281 A
Q0103	331657	TRANS MJ 15022	1	transistor MJ 15022
Q0104	331657	TRANS MJ 15022	1	transistor MJ 15022
Q0105	331657	TRANS MJ 15022	1	transistor MJ 15022
Q0106	331657	TRANS MJ 15022	1	transistor MJ 15022
Q0107	331657	TRANS MJ 15022	1	transistor MJ 15022
Q0108	331657	TRANS MJ 15022	1	transistor MJ 15022
Q0109	348408	TRANS 2SA 1837	1	transistor 2SA 1837
Q0110	351982	TRANS MJL 1302 A	1	transistor MJL 1302 A
Q0111	331658	TRANS MJ 15023	1	transistor MJ 15023
Q0112	331658	TRANS MJ 15023	1	transistor MJ 15023
Q0113	331658	TRANS MJ 15023	1	transistor MJ 15023
Q0114	331658	TRANS MJ 15023	1	transistor MJ 15023
Q0115	331658	TRANS MJ 15023	1	transistor MJ 15023
Q0116	331658	TRANS MJ 15023	1	transistor MJ 15023
Q0117	348409	TRANS 2SC 4793	1	transistor 2SC 4793
Q0118	348421	TRANS 2N 3906	1	transistor 2N 3906
Q0119	335763	TRANS 2N 3904	1	transistor 2N 3904
Q0120	348421	TRANS 2N 3906	1	transistor 2N 3906
Q0121	335763	TRANS 2N 3904	1	transistor 2N 3904
Q0122	348422	TRANS MPSA 42	1	transistor MPSA 42
Q0123	348423	TRANS MPSA 92	1	transistor MPSA 92
Q0124	348423	TRANS MPSA 92	1	transistor MPSA 92
Q0125	348423	TRANS MPSA 92	1	transistor MPSA 92
Q0126	348423	TRANS MPSA 92	1	transistor MPSA 92
Q0127	348422	TRANS MPSA 42	1	transistor MPSA 42
Q0128	307911	TRANS BF 393	1	transistor BF 391
Q0129	307911	TRANS BF 393	1	transistor BF 391
R0010	348906	WI-DR 2X 0.33 OHM 7.00W 5%	1	resistor 2x0.33 Ohm 7watt
R0011	348906	WI-DR 2X 0.33 OHM 7.00W 5%	1	resistor 2x0.33 Ohm 7watt
R0012	348906	WI-DR 2X 0.33 OHM 7.00W 5%	1	resistor 2x0.33 Ohm 7watt
R0013	348906	WI-DR 2X 0.33 OHM 7.00W 5%	1	resistor 2x0.33 Ohm 7watt
R0014	348906	WI-DR 2X 0.33 OHM 7.00W 5%	1	resistor 2x0.33 Ohm 7watt
R0015	348906	WI-DR 2X 0.33 OHM 7.00W 5%	1	resistor 2x0.33 Ohm 7watt
R0042	348593	WI-SO NTC 2.20 KOHM	1	safety component NTC
R0047	348593	WI-SO NTC 2.20 KOHM	1	safety component NTC
R0063	348490	WI-SO NTC 100.00 KOHM	1	safety component NTC
R0068	348490	WI-SO NTC 100.00 KOHM	1	safety component NTC
R0110	348906	WI-DR 2X 0.33 OHM 7.00W 5%	1	resistor 2x0.33 Ohm 7watt
R0111	348906	WI-DR 2X 0.33 OHM 7.00W 5%	1	resistor 2x0.33 Ohm 7watt
R0112	348906	WI-DR 2X 0.33 OHM 7.00W 5%	1	resistor 2x0.33 Ohm 7watt
R0113	348906	WI-DR 2X 0.33 OHM 7.00W 5%	1	resistor 2x0.33 Ohm 7watt
R0114	348906	WI-DR 2X 0.33 OHM 7.00W 5%	1	resistor 2x0.33 Ohm 7watt
R0115	348906	WI-DR 2X 0.33 OHM 7.00W 5%	1	resistor 2x0.33 Ohm 7watt
R0142	348593	WI-SO NTC 2.20 KOHM	1	safety component NTC

	112619	SP 7 SYSTEM-AMP		
Pos. Nr.	Best. Nr.		Menge	
Ref. No.	Part No.	Bezeichnung	Qty	Description
R0147	348593	WI-SO NTC 2.20 KOHM	1	safety component NTC
R0163	348490	WI-SO NTC 100.00 KOHM	1	safety component NTC
R0168	348490	WI-SO NTC 100.00 KOHM	1	safety component NTC
VR001	348675	WI-TRI 2.50 KOHM LIN	1	pot trim 2.5k Ohm lin
VR101	348675	WI-TRI 2.50 KOHM LIN	1	pot trim 2.5k Ohm lin
	813258	PCB-B"XA2600/SP3/5/7	1	PCB assy 81325
AGND	329022	FL.STECKER 6.3/0.8	1	connector 6.3mm faston
B0001	351815	BUCHSE-FL. XLR 3POL PRINTB	1	xlr connector female 3-pole
B0002	351816	STECKER-FL. XLR 3POL PRINTB	1	xlr connector male 3-pin
B0003	351815	BUCHSE-FL. XLR 3POL PRINTB	1	xlr connector female 3-pole
B0004	351816	STECKER-FL. XLR 3POL PRINTB	1	xlr connector male 3-pin
CN001	351565	STIFTLEISTE 6POL MLSS	1	connector male 6-pin
C0001	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C0002	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C0003	301474	KO-EL 22.000MF 16V BIP	1	cap bip electr. 22uF/16V
C0004	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C0005	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C0006	301474	KO-EL 22.000MF 16V BIP	1	cap bip electr. 22uF/16V
C0007	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0008	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0009	301472	KO-EL 10.000MF 63V	1	cap electrolytic 10uF/63V
C0010	301472	KO-EL 10.000MF 63V	1	cap electrolytic 10uF/63V
C0011	329201	KO-KER 0.10MF K 50V 20%	1	cap ceramic 100nF
C0012	329201	KO-KER 0.10MF K 50V 20%	1	cap ceramic 100nF
H0001	343457	DICKS-NETZW. 8PIN 2%	1	res.network 8x10k Ohm
H0002	343457	DICKS-NETZW. 8PIN 2%	1	res.network 8x10k Ohm
I0001	327197	IC NE 5532 P 2FACH OP	1	IC NE 5532 N
I0002	327197	IC NE 5532 P 2FACH OP	1	IC NE 5532 N
R0003	329215	WI-SI 10.00 OHM 0.30W 5%	1	SAFETY RESISTOR 10.0 OHM
R0004	329215	WI-SI 10.00 OHM 0.30W 5%	1	SAFETY RESISTOR 10.0 OHM
	862278	PCBAR#XA2600/PM2600	1	PCB assy 86227
CNOAH	330269	FL.STECKER 6.3/0.8	1	connector 6.3mm faston
CNOAL	330269	FL.STECKER 6.3/0.8	1	connector 6.3mm faston
CNOBH	330269	FL.STECKER 6.3/0.8	1	connector 6.3mm faston
CNOBL	330269	FL.STECKER 6.3/0.8	1	connector 6.3mm faston
CNSER	346200	STIFTLEISTE 2X 7POL	1	connector male 14-pin
CN001	330269	FL.STECKER 6.3/0.8	1	connector 6.3mm faston
CN003	348334	STIFTLEISTE 3POL MLSS	1	connector male 3-pin
CN004	345489	MESSERLST. 6POL	1	connector male 6-pin
CN005	345489	MESSERLST. 6POL	1	connector male 6-pin
CN006	341937	MESSERLST. 4POL	1	connector male 4-pin
CN007	330269	FL.STECKER 6.3/0.8	1	connector 6.3mm faston
CN008	330269	FL.STECKER 6.3/0.8	1	connector 6.3mm faston
CN009	330269	FL.STECKER 6.3/0.8	1	connector 6.3mm faston
CN010	330269	FL.STECKER 6.3/0.8	1	connector 6.3mm faston
CN011	330269	FL.STECKER 6.3/0.8	1	connector 6.3mm faston
CN012	330269	FL.STECKER 6.3/0.8	1	connector 6.3mm faston
CN013	330269	FL.STECKER 6.3/0.8	1	connector 6.3mm faston

	112619	SP 7 SYSTEM-AMP		
Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung	Menge Qty	Description
CN014	330269	FL.STECKER 6.3/0.8	1	connector 6.3mm faston
CN015	330269	FL.STECKER 6.3/0.8	1	connector 6.3mm faston
CN016	330269	FL.STECKER 6.3/0.8	1	connector 6.3mm faston
CN017	330269	FL.STECKER 6.3/0.8	1	connector 6.3mm faston
CN018	330269	FL.STECKER 6.3/0.8	1	connector 6.3mm faston
CN019	330269	FL.STECKER 6.3/0.8	1	connector 6.3mm faston
CN020	330269	FL.STECKER 6.3/0.8	1	connector 6.3mm faston
CN021	348334	STIFTLEISTE 3POL MLSS	1	connector male 3-pin
CN022	348334	STIFTLEISTE 3POL MLSS	1	connector male 3-pin
CN024	330269	FL.STECKER 6.3/0.8	1	connector 6.3mm faston
CN025	330269	FL.STECKER 6.3/0.8	1	connector 6.3mm faston
CN026	330269	FL.STECKER 6.3/0.8	1	connector 6.3mm faston
CN027	330269	FL.STECKER 6.3/0.8	1	connector 6.3mm faston
CN028	330269	FL.STECKER 6.3/0.8	1	connector 6.3mm faston
CN029	330269	FL.STECKER 6.3/0.8	1	connector 6.3mm faston
CN030	330269	FL.STECKER 6.3/0.8	1	connector 6.3mm faston
CN031	330269	FL.STECKER 6.3/0.8	1	connector 6.3mm faston
CN032	330269	FL.STECKER 6.3/0.8	1	connector 6.3mm faston
CN033	330269	FL.STECKER 6.3/0.8	1	connector 6.3mm faston
CN034	330269	FL.STECKER 6.3/0.8	1	connector 6.3mm faston
CN2HI	344862	MESSERLST. 8POL	1	connector male 8-pin
CN2LO	344862	MESSERLST. 8POL	1	connector male 8-pin
CN300	348334	STIFTLEISTE 3POL MLSS	1	connector male 3-pin
CN400	348334	STIFTLEISTE 3POL MLSS	1	connector male 3-pin
CN500	348334	STIFTLEISTE 3POL MLSS	1	connector male 3-pin
CN600	348334	STIFTLEISTE 3POL MLSS	1	connector male 3-pin
CN701	348334	STIFTLEISTE 3POL MLSS	1	connector male 3-pin
CN702	348334	STIFTLEISTE 3POL MLSS	1	connector male 3-pin
CN703	348334	STIFTLEISTE 3POL MLSS	1	connector male 3-pin
CN704	348334	STIFTLEISTE 3POL MLSS	1	connector male 3-pin
CN8HI	348334	STIFTLEISTE 3POL MLSS	1	connector male 3-pin
CN8LO	348334	STIFTLEISTE 3POL MLSS	1	connector male 3-pin
C0001	341714	KO-SO 0.100MF 275V K 20%	1	safety cap 100nF/275V
C0002	341714	KO-SO 0.100MF 275V K 20%	1	safety cap 100nF/275V
C0003	340988	KO-FOL 0.470MF 63V 5%	1	cap mylar 470nF
C0004	342967	KO-FOL 3.300MF 50V 10%	1	cap mylar 3.3uF
C0005	342923	KO-FOL 0.220MF 63V 5%	1	cap mylar 220nF
C0006	351835	KO-EL 4700.000MF 100V	1	cap electrolytic 4700uF/100
C0007	351835	KO-EL 4700.000MF 100V	1	cap electrolytic 4700uF/100
C0008	351835	KO-EL 4700.000MF 100V	1	cap electrolytic 4700uF/100
C0009	351835	KO-EL 4700.000MF 100V	1	cap electrolytic 4700uF/100
C0010	351835	KO-EL 4700.000MF 100V	1	cap electrolytic 4700uF/100
C0011	351835	KO-EL 4700.000MF 100V	1	cap electrolytic 4700uF/100
C0012	351835	KO-EL 4700.000MF 100V	1	cap electrolytic 4700uF/100
C0013	351835	KO-EL 4700.000MF 100V	1	cap electrolytic 4700uF/100
C0014	327366	KO-EL 4.700MF 50V BIP	1	cap bip electr. 4.7uF/50V
C0015	329201	KO-KER 0.10MF K 50V 20%	1	cap ceramic 100nF
C0016	329201	KO-KER 0.10MF K 50V 20%	1	cap ceramic 100nF
C0301	343532	KO-EL 100.000MF 25V	1	cap electrolytic 100uF/25V
C0302	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0303	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0304	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF

	112619	SP 7 SYSTEM-AMP		
Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung	Menge Qty	Description
C0305	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0306	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0307	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0308	343532	KO-EL 100.000MF 25V	1	cap electrolytic 100uF/25V
C0309	304349	KO-EL 2.200MF 50V BIP	1	cap bip electr. 2.2uF/50V
C0310	301530	KO-KER 100.0PF 500V 10%	1	cap ceramic 100pF
C0311	340988	KO-FOL 0.470MF 63V 5%	1	cap mylar 470nF
C0312	340988	KO-FOL 0.470MF 63V 5%	1	cap mylar 470nF
C0313	343533	KO-EL 220.000MF 25V	1	cap electrolytic 220uF/25V
C0314	335787	KO-KER 15.0PF 100V 2%	1	cap ceramic 15pF
C0315	343532	KO-EL 100.000MF 25V	1	cap electrolytic 100uF/25V
C0316	343532	KO-EL 100.000MF 25V	1	cap electrolytic 100uF/25V
C0317	327390	KO-FOL 470.000PF 100V 5%	1	cap mylar 470pF
C0318	306059	KO-KER 3.9PF 500V0.25	1	cap ceramic 3.9pF
C0319	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C0320	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C0321	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0322	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0323	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C0324	335787	KO-KER 15.0PF 100V 2%	1	cap ceramic 15pF
C0325	304349	KO-EL 2.200MF 50V BIP	1	cap bip electr. 2.2uF/50V
C0326	304349	KO-EL 2.200MF 50V BIP	1	cap bip electr. 2.2uF/50V
C0385	341714	KO-SO 0.100MF 275V K 20%	1	safety cap 100nF/275V
C0386	341714	KO-SO 0.100MF 275V K 20%	1	safety cap 100nF/275V
C0387	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C0388	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C0389	301474	KO-EL 22.000MF 16V BIP	1	cap bip electr. 22uF/16V
C0401	343532	KO-EL 100.000MF 25V	1	cap electrolytic 100uF/25V
C0402	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0403	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0404	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0405	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0406	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0407	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0408	343532	KO-EL 100.000MF 25V	1	cap electrolytic 100uF/25V
C0409	304349	KO-EL 2.200MF 50V BIP	1	cap bip electr. 2.2uF/50V
C0410	301530	KO-KER 100.0PF 500V 10%	1	cap ceramic 100pF
C0411	340988	KO-FOL 0.470MF 63V 5%	1	cap mylar 470nF
C0412	340988	KO-FOL 0.470MF 63V 5%	1	cap mylar 470nF
C0413	343533	KO-EL 220.000MF 25V	1	cap electrolytic 220uF/25V
C0414	335787	KO-KER 15.0PF 100V 2%	1	cap ceramic 15pF
C0415	343532	KO-EL 100.000MF 25V	1	cap electrolytic 100uF/25V
C0416	343532	KO-EL 100.000MF 25V	1	cap electrolytic 100uF/25V
C0417	327390	KO-FOL 470.000PF 100V 5%	1	cap mylar 470pF
C0418	306059	KO-KER 3.9PF 500V0.25	1	cap ceramic 3.9pF
C0419	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C0420	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C0421	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0422	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0423	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C0424	335787	KO-KER 15.0PF 100V 2%	1	cap ceramic 15pF
C0425	304349	KO-EL 2.200MF 50V BIP	1	cap bip electr. 2.2uF/50V

	112619	SP 7 SYSTEM-AMP		
Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung	Menge Qty	Description
C0426	304349	KO-EL 2.200MF 50V BIP	1	cap bip electr. 2.2uF/50V
C0485	341714	KO-SO 0.100MF 275V K 20%	1	safety cap 100nF/275V
C0486	341714	KO-SO 0.100MF 275V K 20%	1	safety cap 100nF/275V
C0487	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C0488	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C0489	301474	KO-EL 22.000MF 16V BIP	1	cap bip electr. 22uF/16V
C0501	343532	KO-EL 100.000MF 25V	1	cap electrolytic 100uF/25V
C0502	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0503	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0504	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0505	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0506	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0507	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0508	343532	KO-EL 100.000MF 25V	1	cap electrolytic 100uF/25V
C0509	304349	KO-EL 2.200MF 50V BIP	1	cap bip electr. 2.2uF/50V
C0510	301530	KO-KER 100.0PF 500V 10%	1	cap ceramic 100pF
C0511	340988	KO-FOL 0.470MF 63V 5%	1	cap mylar 470nF
C0512	340988	KO-FOL 0.470MF 63V 5%	1	cap mylar 470nF
C0513	343533	KO-EL 220.000MF 25V	1	cap electrolytic 220uF/25V
C0514	335787	KO-KER 15.0PF 100V 2%	1	cap ceramic 15pF
C0515	343532	KO-EL 100.000MF 25V	1	cap electrolytic 100uF/25V
C0516	343532	KO-EL 100.000MF 25V	1	cap electrolytic 100uF/25V
C0517	327390	KO-FOL 470.000PF 100V 5%	1	cap mylar 470pF
C0518	306059	KO-KER 3.9PF 500V0.25	1	cap ceramic 3.9pF
C0519	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C0520	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C0521	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0522	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0523	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C0524	335787	KO-KER 15.0PF 100V 2%	1	cap ceramic 15pF
C0525	304349	KO-EL 2.200MF 50V BIP	1	cap bip electr. 2.2uF/50V
C0526	304349	KO-EL 2.200MF 50V BIP	1	cap bip electr. 2.2uF/50V
C0585	341714	KO-SO 0.100MF 275V K 20%	1	safety cap 100nF/275V
C0586	341714	KO-SO 0.100MF 275V K 20%	1	safety cap 100nF/275V
C0587	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C0588	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C0589	301474	KO-EL 22.000MF 16V BIP	1	cap bip electr. 22uF/16V
C0601	343532	KO-EL 100.000MF 25V	1	cap electrolytic 100uF/25V
C0602	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0603	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0604	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0605	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0606	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0607	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0608	343532	KO-EL 100.000MF 25V	1	cap electrolytic 100uF/25V
C0609	304349	KO-EL 2.200MF 50V BIP	1	cap bip electr. 2.2uF/50V
C0610	301530	KO-KER 100.0PF 500V 10%	1	cap ceramic 100pF
C0611	340988	KO-FOL 0.470MF 63V 5%	1	cap mylar 470nF
C0612	340988	KO-FOL 0.470MF 63V 5%	1	cap mylar 470nF
C0613	343533	KO-EL 220.000MF 25V	1	cap electrolytic 220uF/25V
C0614	335787	KO-KER 15.0PF 100V 2%	1	cap ceramic 15pF
C0615	343532	KO-EL 100.000MF 25V	1	cap electrolytic 100uF/25V

	112619	SP 7 SYSTEM-AMP		
Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung	Menge Qty	Description
C0616	343532	KO-EL 100.000MF 25V	1	cap electrolytic 100uF/25V
C0617	327390	KO-FOL 470.000PF 100V 5%	1	cap mylar 470pF
C0618	306059	KO-KER 3.9PF 500V0.25	1	cap ceramic 3.9pF
C0619	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C0620	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C0621	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0622	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0623	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C0624	335787	KO-KER 15.0PF 100V 2%	1	cap ceramic 15pF
C0625	304349	KO-EL 2.200MF 50V BIP	1	cap bip electr. 2.2uF/50V
C0626	304349	KO-EL 2.200MF 50V BIP	1	cap bip electr. 2.2uF/50V
C0685	341714	KO-SO 0.100MF 275V K 20%	1	safety cap 100nF/275V
C0686	341714	KO-SO 0.100MF 275V K 20%	1	safety cap 100nF/275V
C0687	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C0688	301558	KO-KER 33.0PF 100V 2%	1	cap ceramic 33pF
C0689	301474	KO-EL 22.000MF 16V BIP	1	cap bip electr. 22uF/16V
C0700	337597	KO-EL 1000.000MF 50V	1	cap electrolytic 1000uF/50V
C0701	301524	KO-KER 47.0PF 500V 10%	1	cap ceramic 47pF
C0702	343530	KO-EL 47.000MF 50V	1	cap electrolytic 47uF/50V
C0703	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0704	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0705	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0706	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0707	340244	KO-FOL 0.330MF 63V 5%	1	cap mylar 330nF
C0708	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0709	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0800	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0801	301472	KO-EL 10.000MF 63V	1	cap electrolytic 10uF/63V
C0802	301472	KO-EL 10.000MF 63V	1	cap electrolytic 10uF/63V
C0803	301524	KO-KER 47.0PF 500V 10%	1	cap ceramic 47pF
C0804	301524	KO-KER 47.0PF 500V 10%	1	cap ceramic 47pF
C0805	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0806	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0807	337597	KO-EL 1000.000MF 50V	1	cap electrolytic 1000uF/50V
C0808	337597	KO-EL 1000.000MF 50V	1	cap electrolytic 1000uF/50V
D0001	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0002	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0003	304360	DIODE 1N 4007 GEGURTET	1	diode 1N 4002
D0004	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0005	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0006	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0007	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0301	309450	DIODZ BZX 55C 15V 0.50W	1	diode zener 15V
D0302	309450	DIODZ BZX 55C 15V 0.50W	1	diode zener 15V
D0303	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0304	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0305	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0306	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0307	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0308	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0309	329511	DIODZ BZX 55C 2V4 0.50W	1	diode zener 2V4
D0385	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148

	112619	SP 7 SYSTEM-AMP		
Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung	Menge Qty	Description
D0401	309450	DIODZ BZX 55C 15V 0.50W	1	diode zener 15V
D0402	309450	DIODZ BZX 55C 15V 0.50W	1	diode zener 15V
D0403	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0404	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0405	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0406	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0407	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0408	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0409	329511	DIODZ BZX 55C 2V4 0.50W	1	diode zener 2V4
D0485	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0501	309450	DIODZ BZX 55C 15V 0.50W	1	diode zener 15V
D0502	309450	DIODZ BZX 55C 15V 0.50W	1	diode zener 15V
D0503	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0504	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0505	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0506	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0507	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0508	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0509	329511	DIODZ BZX 55C 2V4 0.50W	1	diode zener 2V4
D0585	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0601	309450	DIODZ BZX 55C 15V 0.50W	1	diode zener 15V
D0602	309450	DIODZ BZX 55C 15V 0.50W	1	diode zener 15V
D0603	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0604	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0605	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0606	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0607	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0608	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0609	329511	DIODZ BZX 55C 2V4 0.50W	1	diode zener 2V4
D0685	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0701	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0702	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0703	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0704	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0705	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0706	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0707	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0708	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0709	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0800	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0801	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0802	304992	DIODZ BZX 55C 6V8 0.50W	1	diode zener 6V8
D0803	304992	DIODZ BZX 55C 6V8 0.50W	1	diode zener 6V8
D0804	304360	DIODE 1N 4007 GEGURTET	1	diode 1N 4002
E0001	354859	RELAIS 793-P-1C-S 24VDC	1	relay 24V
E0002	356594	RELAIS 793-P-1A-S-TV10	1	relay 24V / spst
E0003	354859	RELAIS 793-P-1C-S 24VDC	1	relay 24V
E0385	354859	RELAIS 793-P-1C-S 24VDC	1	relay 24V
E0485	354859	RELAIS 793-P-1C-S 24VDC	1	relay 24V
E0585	354859	RELAIS 793-P-1C-S 24VDC	1	relay 24V
E0685	354859	RELAIS 793-P-1C-S 24VDC	1	relay 24V
F0001	328891	SICHER T 12.500 A/250V	1	fuse 12.5A slow blow

	112619	SP 7 SYSTEM-AMP		
Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung	Menge Qty	Description
F0002	328891	SICHER T 12.500 A/250V	1	fuse 12.5A slow blow
F0700	302583	SICHER T 1.600 A/250V	1	fuse 1.6A slow blow
F0800	302583	SICHER T 1.600 A/250V	1	fuse 1.6A slow blow
F0801	302583	SICHER T 1.600 A/250V	1	fuse 1.6A slow blow
GNDAH	330269	FL.STECKER 6.3/0.8	1	connector 6.3mm faston
GNDAL	330269	FL.STECKER 6.3/0.8	1	connector 6.3mm faston
GNDBH	330269	FL.STECKER 6.3/0.8	1	connector 6.3mm faston
GNDBL	330269	FL.STECKER 6.3/0.8	1	connector 6.3mm faston
G0700	331965	GLRI B 80 C1500	1	rectifier B80 C1500
G0800	331965	GLRI B 80 C1500	1	rectifier B80 C1500
H0300	343457	DICKS-NETZW. 8PIN 2%	1	res.network 8x10k Ohm
H0301	343457	DICKS-NETZW. 8PIN 2%	1	res.network 8x10k Ohm
H0400	343457	DICKS-NETZW. 8PIN 2%	1	res.network 8x10k Ohm
H0401	343457	DICKS-NETZW. 8PIN 2%	1	res.network 8x10k Ohm
H0500	343457	DICKS-NETZW. 8PIN 2%	1	res.network 8x10k Ohm
H0501	343457	DICKS-NETZW. 8PIN 2%	1	res.network 8x10k Ohm
H0600	343457	DICKS-NETZW. 8PIN 2%	1	res.network 8x10k Ohm
H0601	343457	DICKS-NETZW. 8PIN 2%	1	res.network 8x10k Ohm
I0301	338359	IC OP 07 CP	1	IC LM 308 A
I0302	327197	IC NE 5532 P 2FACH OP	1	IC NE 5532 N
I0303	307421	IC CA 3080 E OTA	1	IC CA 3080 E
I0304	331340	IC TL 072 CP 2FACH OP	1	IC TL 072 CP
I0305	327197	IC NE 5532 P 2FACH OP	1	IC NE 5532 N
I0401	338359	IC OP 07 CP	1	IC LM 308 A
I0402	327197	IC NE 5532 P 2FACH OP	1	IC NE 5532 N
I0403	307421	IC CA 3080 E OTA	1	IC CA 3080 E
I0404	331340	IC TL 072 CP 2FACH OP	1	IC TL 072 CP
I0405	327197	IC NE 5532 P 2FACH OP	1	IC NE 5532 N
I0501	338359	IC OP 07 CP	1	IC LM 308 A
I0502	327197	IC NE 5532 P 2FACH OP	1	IC NE 5532 N
I0503	307421	IC CA 3080 E OTA	1	IC CA 3080 E
I0504	331340	IC TL 072 CP 2FACH OP	1	IC TL 072 CP
I0505	327197	IC NE 5532 P 2FACH OP	1	IC NE 5532 N
I0601	338359	IC OP 07 CP	1	IC LM 308 A
I0602	327197	IC NE 5532 P 2FACH OP	1	IC NE 5532 N
I0603	307421	IC CA 3080 E OTA	1	IC CA 3080 E
I0604	331340	IC TL 072 CP 2FACH OP	1	IC TL 072 CP
I0605	327197	IC NE 5532 P 2FACH OP	1	IC NE 5532 N
I0700	331340	IC TL 072 CP 2FACH OP	1	IC TL 072 CP
I0701	332985	IC TL 074 CN	1	IC TL 074 CN
L0385	348592	FILTERSP. 2.50UH/0.004OHM	1	coil 2.5uH
L0485	348592	FILTERSP. 2.50UH/0.004OHM	1	coil 2.5uH
L0585	348592	FILTERSP. 2.50UH/0.004OHM	1	coil 2.5uH
L0685	348592	FILTERSP. 2.50UH/0.004OHM	1	coil 2.5uH
OUTAH	330269	FL.STECKER 6.3/0.8	1	connector 6.3mm faston
OUTAL	330269	FL.STECKER 6.3/0.8	1	connector 6.3mm faston
OUTBH	330269	FL.STECKER 6.3/0.8	1	connector 6.3mm faston
OUTBL	330269	FL.STECKER 6.3/0.8	1	connector 6.3mm faston
Q0001	301257	TRANS BD 135-10 SOT-32	1	transistor BD 135-10
Q0002	306928	TRANS BC 560 C	1	transistor BC 560 C
Q0003	306928	TRANS BC 560 C	1	transistor BC 560 C
Q0004	307150	TRANS BC 337-25 TO 92	1	transistor BC 337-25

	112619	SP 7 SYSTEM-AMP		
Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung	Menge Qty	Description
Q0005	306928	TRANS BC 560 C	1	transistor BC 560 C
Q0006	306928	TRANS BC 560 C	1	transistor BC 560 C
Q0007	301184	TRANS BC 550 C	1	transistor BC 550 B
Q0008	306928	TRANS BC 560 C	1	transistor BC 560 C
Q0009	306928	TRANS BC 560 C	1	transistor BC 560 C
Q0010	306928	TRANS BC 560 C	1	transistor BC 560 C
Q0011	306928	TRANS BC 560 C	1	transistor BC 560 C
Q0300	338869	TRANS MJE 350	1	transistor MJE 350
Q0301	335763	TRANS 2N 3904	1	transistor 2N 3904
Q0302	348422	TRANS MPSA 42	1	transistor MPSA 42
Q0303	348422	TRANS MPSA 42	1	transistor MPSA 42
Q0304	335763	TRANS 2N 3904	1	transistor 2N 3904
Q0305	335763	TRANS 2N 3904	1	transistor 2N 3904
Q0306	335763	TRANS 2N 3904	1	transistor 2N 3904
Q0307	348421	TRANS 2N 3906	1	transistor 2N 3906
Q0308	348421	TRANS 2N 3906	1	transistor 2N 3906
Q0309	348421	TRANS 2N 3906	1	transistor 2N 3906
Q0310	348423	TRANS MPSA 92	1	transistor MPSA 92
Q0311	348423	TRANS MPSA 92	1	transistor MPSA 92
Q0312	338868	TRANS MJE 340	1	transistor MJE 340
Q0313	348421	TRANS 2N 3906	1	transistor 2N 3906
Q0314	335763	TRANS 2N 3904	1	transistor 2N 3904
Q0315	348421	TRANS 2N 3906	1	transistor 2N 3906
Q0316	330264	TRANS J 111	1	transistor J 111 A
Q0386	348421	TRANS 2N 3906	1	transistor 2N 3906
Q0387	335763	TRANS 2N 3904	1	transistor 2N 3904
Q0388	348421	TRANS 2N 3906	1	transistor 2N 3906
Q0400	338869	TRANS MJE 350	1	transistor MJE 350
Q0401	335763	TRANS 2N 3904	1	transistor 2N 3904
Q0402	348422	TRANS MPSA 42	1	transistor MPSA 42
Q0403	348422	TRANS MPSA 42	1	transistor MPSA 42
Q0404	335763	TRANS 2N 3904	1	transistor 2N 3904
Q0405	335763	TRANS 2N 3904	1	transistor 2N 3904
Q0406	335763	TRANS 2N 3904	1	transistor 2N 3904
Q0407	348421	TRANS 2N 3906	1	transistor 2N 3906
Q0408	348421	TRANS 2N 3906	1	transistor 2N 3906
Q0409	348421	TRANS 2N 3906	1	transistor 2N 3906
Q0410	348423	TRANS MPSA 92	1	transistor MPSA 92
Q0411	348423	TRANS MPSA 92	1	transistor MPSA 92
Q0412	338868	TRANS MJE 340	1	transistor MJE 340
Q0413	348421	TRANS 2N 3906	1	transistor 2N 3906
Q0414	335763	TRANS 2N 3904	1	transistor 2N 3904
Q0415	348421	TRANS 2N 3906	1	transistor 2N 3906
Q0416	330264	TRANS J 111	1	transistor J 111 A
Q0486	348421	TRANS 2N 3906	1	transistor 2N 3906
Q0487	335763	TRANS 2N 3904	1	transistor 2N 3904
Q0488	348421	TRANS 2N 3906	1	transistor 2N 3906
Q0500	338869	TRANS MJE 350	1	transistor MJE 350
Q0501	335763	TRANS 2N 3904	1	transistor 2N 3904
Q0502	348422	TRANS MPSA 42	1	transistor MPSA 42
Q0503	348422	TRANS MPSA 42	1	transistor MPSA 42
Q0504	335763	TRANS 2N 3904	1	transistor 2N 3904

	112619	SP 7 SYSTEM-AMP			
Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung	Menge Qty	Description	
Q0505	335763	TRANS 2N 3904	1	transistor 2N 3904	
Q0506	335763	TRANS 2N 3904	1	transistor 2N 3904	
Q0507	348421	TRANS 2N 3906	1	transistor 2N 3906	
Q0508	348421	TRANS 2N 3906	1	transistor 2N 3906	
Q0509	348421	TRANS 2N 3906	1	transistor 2N 3906	
Q0510	348423	TRANS MPSA 92	1	transistor MPSA 92	
Q0511	348423	TRANS MPSA 92	1	transistor MPSA 92	
Q0512	338868	TRANS MJE 340	1	transistor MJE 340	
Q0513	348421	TRANS 2N 3906	1	transistor 2N 3906	
Q0514	335763	TRANS 2N 3904	1	transistor 2N 3904	
Q0515	348421	TRANS 2N 3906	1	transistor 2N 3906	
Q0516	330264	TRANS J 111	1	transistor J 111 A	
Q0586	348421	TRANS 2N 3906	1	transistor 2N 3906	
Q0587	335763	TRANS 2N 3904	1	transistor 2N 3904	
Q0588	348421	TRANS 2N 3906	1	transistor 2N 3906	
Q0600	338869	TRANS MJE 350	1	transistor MJE 350	
Q0601	335763	TRANS 2N 3904	1	transistor 2N 3904	
Q0602	348422	TRANS MPSA 42	1	transistor MPSA 42	
Q0603	348422	TRANS MPSA 42	1	transistor MPSA 42	
Q0604	335763	TRANS 2N 3904	1	transistor 2N 3904	
Q0605	335763	TRANS 2N 3904	1	transistor 2N 3904	
Q0606	335763	TRANS 2N 3904	1	transistor 2N 3904	
Q0607	348421	TRANS 2N 3906	1	transistor 2N 3906	
Q0608	348421	TRANS 2N 3906	1	transistor 2N 3906	
Q0609	348421	TRANS 2N 3906	1	transistor 2N 3906	
Q0610	348423	TRANS MPSA 92	1	transistor MPSA 92	
Q0611	348423	TRANS MPSA 92	1	transistor MPSA 92	
Q0612	338868	TRANS MJE 340	1	transistor MJE 340	
Q0613	348421	TRANS 2N 3906	1	transistor 2N 3906	
Q0614	335763	TRANS 2N 3904	1	transistor 2N 3904	
Q0615	348421	TRANS 2N 3906	1	transistor 2N 3906	
Q0616	330264	TRANS J 111	1	transistor J 111 A	
Q0686	348421	TRANS 2N 3906	1	transistor 2N 3906	
Q0687	335763	TRANS 2N 3904	1	transistor 2N 3904	
Q0688	348421	TRANS 2N 3906	1	transistor 2N 3906	
Q0700	304591	TRANS BD 245 C	1	transistor BD 245 C	
Q0701	307150	TRANS BC 337-25 TO 92	1	transistor BC 337-25	
Q0702	307150	TRANS BC 337-25 TO 92	1	transistor BC 337-25	
Q0703	301184	TRANS BC 550 C	1	transistor BC 550 B	
Q0704	301184	TRANS BC 550 C	1	transistor BC 550 B	
Q0705	301184	TRANS BC 550 C	1	transistor BC 550 B	
Q0706	301184	TRANS BC 550 C	1	transistor BC 550 B	
Q0707	301184	TRANS BC 550 C	1	transistor BC 550 B	
Q0800	304591	TRANS BD 245 C	1	transistor BD 245 C	
Q0801	307150	TRANS BC 337-25 TO 92	1	transistor BC 337-25	
Q0802	307150	TRANS BC 337-25 TO 92	1	transistor BC 337-25	
Q0803	307430	TRANS BC 327-25 TO 92	1	transistor BC 327-25	
Q0804	307430	TRANS BC 327-25 TO 92	1	transistor BC 327-25	
Q0805	304592	TRANS BD 246 C	1	transistor BD 246 C	
R0001	348550	WI-SO NTC 10.00 OHM K	1	resistor ntc 10 Ohm	
R0002	348550	WI-SO NTC 10.00 OHM K	1	resistor ntc 10 Ohm	
R0302	334910	WI-SCH 6.20 KOHM 2.00W 5%	1	resistor 6.2k Ohm 2watt	

	112619	SP 7 SYSTEM-AMP			
Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung	Menge Qty	Description	
R0305	329215	WI-SI 10.00 OHM 0.30W 5%	1	SAFETY RESISTOR 10.0 OHM	
R0325	329215	WI-SI 10.00 OHM 0.30W 5%	1	SAFETY RESISTOR 10.0 OHM	
R0330	334910	WI-SCH 6.20 KOHM 2.00W 5%	1	resistor 6.2k Ohm 2watt	
R0385	341713	WI-DR 4.70 OHM 4.00W 5%	1	resistor 4.70 Ohm 4watt	
R0386	348590	WI-DR 8.20 OHM 4.00W 5%	1	resistor 8.20 Ohm 4watt	
R0387	348590	WI-DR 8.20 OHM 4.00W 5%	1	resistor 8.20 Ohm 4watt	
R0388	348590	WI-DR 8.20 OHM 4.00W 5%	1	resistor 8.20 Ohm 4watt	
R0389	348590	WI-DR 8.20 OHM 4.00W 5%	1	resistor 8.20 Ohm 4watt	
R0402	334910	WI-SCH 6.20 KOHM 2.00W 5%	1	resistor 6.2k Ohm 2watt	
R0405	329215	WI-SI 10.00 OHM 0.30W 5%	1	SAFETY RESISTOR 10.0 OHM	
R0425	329215	WI-SI 10.00 OHM 0.30W 5%	1	SAFETY RESISTOR 10.0 OHM	
R0430	334910	WI-SCH 6.20 KOHM 2.00W 5%	1	resistor 6.2k Ohm 2watt	
R0485	341713	WI-DR 4.70 OHM 4.00W 5%	1	resistor 4.70 Ohm 4watt	
R0486	348590	WI-DR 8.20 OHM 4.00W 5%	1	resistor 8.20 Ohm 4watt	
R0487	348590	WI-DR 8.20 OHM 4.00W 5%	1	resistor 8.20 Ohm 4watt	
R0488	348590	WI-DR 8.20 OHM 4.00W 5%	1	resistor 8.20 Ohm 4watt	
R0489	348590	WI-DR 8.20 OHM 4.00W 5%	1	resistor 8.20 Ohm 4watt	
R0502	334910	WI-SCH 6.20 KOHM 2.00W 5%	1	resistor 6.2k Ohm 2watt	
R0505	329215	WI-SI 10.00 OHM 0.30W 5%	1	SAFETY RESISTOR 10.0 OHM	
R0525	329215	WI-SI 10.00 OHM 0.30W 5%	1	SAFETY RESISTOR 10.0 OHM	
R0530	334910	WI-SCH 6.20 KOHM 2.00W 5%	1	resistor 6.2k Ohm 2watt	
R0585	341713	WI-DR 4.70 OHM 4.00W 5%	1	resistor 4.70 Ohm 4watt	
R0586	348590	WI-DR 8.20 OHM 4.00W 5%	1	resistor 8.20 Ohm 4watt	
R0587	348590	WI-DR 8.20 OHM 4.00W 5%	1	resistor 8.20 Ohm 4watt	
R0588	348590	WI-DR 8.20 OHM 4.00W 5%	1	resistor 8.20 Ohm 4watt	
R0589	348590	WI-DR 8.20 OHM 4.00W 5%	1	resistor 8.20 Ohm 4watt	
R0602	334910	WI-SCH 6.20 KOHM 2.00W 5%	1	resistor 6.2k Ohm 2watt	
R0605	329215	WI-SI 10.00 OHM 0.30W 5%	1	SAFETY RESISTOR 10.0 OHM	
R0625	329215	WI-SI 10.00 OHM 0.30W 5%	1	SAFETY RESISTOR 10.0 OHM	
R0630	334910	WI-SCH 6.20 KOHM 2.00W 5%	1	resistor 6.2k Ohm 2watt	
R0685	341713	WI-DR 4.70 OHM 4.00W 5%	1	resistor 4.70 Ohm 4watt	
R0686	348590	WI-DR 8.20 OHM 4.00W 5%	1	resistor 8.20 Ohm 4watt	
R0687	348590	WI-DR 8.20 OHM 4.00W 5%	1	resistor 8.20 Ohm 4watt	
R0688	348590	WI-DR 8.20 OHM 4.00W 5%	1	resistor 8.20 Ohm 4watt	
R0689	348590	WI-DR 8.20 OHM 4.00W 5%	1	resistor 8.20 Ohm 4watt	
R0806	301676	WI-DR 10.00 OHM 5.00W 5%	1	resistor 10.0 Ohm 5watt	
R0809	301676	WI-DR 10.00 OHM 5.00W 5%	1	resistor 10.0 Ohm 5watt	
S0001	327947	SCHALTELEMENT C42315-A1347-	0	switch element on/off	
S0003	338886	SCHALTER-SCHIEBE 2XUM	1	switch slide	
S0300	327947	SCHALTELEMENT C42315-A1347-	0	switch element on/off	
S0400	327947	SCHALTELEMENT C42315-A1347-	0	switch element on/off	
S0500	327947	SCHALTELEMENT C42315-A1347-	0	switch element on/off	
S0600	327947	SCHALTELEMENT C42315-A1347-	0	switch element on/off	
S0700	327947	SCHALTELEMENT C42315-A1347-	0	switch element on/off	
VR300	348486	WI-TRI 47.00 KOHM LIN	1	pot trim 47k Ohm lin	
VR400	348486	WI-TRI 47.00 KOHM LIN	1	pot trim 47k Ohm lin	
VR500	348486	WI-TRI 47.00 KOHM LIN	1	pot trim 47k Ohm lin	
VR600	348486	WI-TRI 47.00 KOHM LIN	1	pot trim 47k Ohm lin	
VR700	348675	WI-TRI 2.50 KOHM LIN	1	pot trim 2.5k Ohm lin	
	306838	SICHER-HALTER FAP	1	fuse holder	
	306838	SICHER-HALTER FAP	1	fuse holder	
	306838	SICHER-HALTER FAP	1	fuse holder	

	112619	SP 7 SYSTEM-AMP		
Pos. Nr.	Best. Nr.		Menge	
Ref. No.	Part No.	Bezeichnung	Qty	Description
	328390	SICHER-HALTER FAU	2	fuse holder
	328391	SICHER-HALTER-KAPPE FEK	2	fuse holder carrier
	871358	PCB-A"XA2600/SP3/5/7 N 4	1	PCB assy 87135
CN08X	349105	MESSERLST. 20POL	1	connector male 20-pin
D0026	336398	LED GN 3MM TLHG 4400/01	1	LED green 3mm
D0027	336398	LED GN 3MM TLHG 4400/01	1	LED green 3mm
D0036	336398	LED GN 3MM TLHG 4400/01	1	LED green 3mm
D0037	336398	LED GN 3MM TLHG 4400/01	1	LED green 3mm
D0046	336398	LED GN 3MM TLHG 4400/01	1	LED green 3mm
D0056	336398	LED GN 3MM TLHG 4400/01	1	LED green 3mm
D0066	336398	LED GN 3MM TLHG 4400/01	1	LED green 3mm
D0076	336398	LED GN 3MM TLHG 4400/01	1	LED green 3mm
D0081	336399	LED RT 3MM TLUR 4401	1	LED red 3mm
D0082	336397	LED GE 3MM TLHY 4400/01	1	LED yellow 3mm
D0083	336397	LED GE 3MM TLHY 4400/01	1	LED yellow 3mm
D0084	336397	LED GE 3MM TLHY 4400/01	1	LED yellow 3mm
D0085	336398	LED GN 3MM TLHG 4400/01	1	LED green 3mm
D0086	336397	LED GE 3MM TLHY 4400/01	1	LED yellow 3mm
D0087	336397	LED GE 3MM TLHY 4400/01	1	LED yellow 3mm
	822208	PCB-A#SP 7	1	PCB assy 82220
CN008	349105	MESSERLST. 20POL	1	connector male 20-pin
CN01X	351565	STIFTELEISTE 6POL MLSS	1	connector male 6-pin
CN03X	348334	STIFTELEISTE 3POL MLSS	1	connector male 3-pin
CN04X	345489	MESSERLST. 6POL	1	connector male 6-pin
CN05X	345489	MESSERLST. 6POL	1	connector male 6-pin
CN06X	341937	MESSERLST. 4POL	1	connector male 4-pin
CN300	348334	STIFTELEISTE 3POL MLSS	1	connector male 3-pin
CN400	348334	STIFTELEISTE 3POL MLSS	1	connector male 3-pin
CN500	348334	STIFTELEISTE 3POL MLSS	1	connector male 3-pin
CN600	348334	STIFTELEISTE 3POL MLSS	1	connector male 3-pin
C0001	301472	KO-EL 10.000MF 63V	1	cap electrolytic 10uF/63V
C0002	301472	KO-EL 10.000MF 63V	1	cap electrolytic 10uF/63V
C0003	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0004	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0005	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0006	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0007	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0008	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0009	301472	KO-EL 10.000MF 63V	1	cap electrolytic 10uF/63V
C0010	301472	KO-EL 10.000MF 63V	1	cap electrolytic 10uF/63V
C0011	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0012	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0013	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0014	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0015	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0016	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0020	304349	KO-EL 2.200MF 50V BIP	1	cap bip electr. 2.2uF/50V
C0021	343530	KO-EL 47.000MF 50V	1	cap electrolytic 47uF/50V

	112619	SP 7 SYSTEM-AMP		
Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung	Menge Qty	Description
C0022	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0023	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0024	301472	KO-EL 10.000MF 63V	1	cap electrolytic 10uF/63V
C0025	301472	KO-EL 10.000MF 63V	1	cap electrolytic 10uF/63V
C0030	304349	KO-EL 2.200MF 50V BIP	1	cap bip electr. 2.2uF/50V
C0031	343530	KO-EL 47.000MF 50V	1	cap electrolytic 47uF/50V
C0040	304349	KO-EL 2.200MF 50V BIP	1	cap bip electr. 2.2uF/50V
C0041	343530	KO-EL 47.000MF 50V	1	cap electrolytic 47uF/50V
C0050	304349	KO-EL 2.200MF 50V BIP	1	cap bip electr. 2.2uF/50V
C0051	343530	KO-EL 47.000MF 50V	1	cap electrolytic 47uF/50V
C0060	304349	KO-EL 2.200MF 50V BIP	1	cap bip electr. 2.2uF/50V
C0061	343530	KO-EL 47.000MF 50V	1	cap electrolytic 47uF/50V
C0062	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0063	329021	KO-KER 0.10MF 100V 20%	1	cap ceramic 100nF
C0070	304349	KO-EL 2.200MF 50V BIP	1	cap bip electr. 2.2uF/50V
C0071	343530	KO-EL 47.000MF 50V	1	cap electrolytic 47uF/50V
C0102	342933	KO-FOL 0.022MF 100V 5%	1	cap mylar 22nF
C0103	344109	KO-FOL 0.056MF 63V 5%	1	cap mylar 56nF
C0104	327389	KO-FOL 220.000PF 100V 5%	1	cap mylar 220pF
C0105	330055	KO-FOL 180.000PF 100V 5%	1	cap mylar 180pF
C0202	342933	KO-FOL 0.022MF 100V 5%	1	cap mylar 22nF
C0203	344109	KO-FOL 0.056MF 63V 5%	1	cap mylar 56nF
C0204	327389	KO-FOL 220.000PF 100V 5%	1	cap mylar 220pF
C0205	330055	KO-FOL 180.000PF 100V 5%	1	cap mylar 180pF
C0301	332962	KO-EL 470.000MF 25V	1	cap electrolytic 470uF/25V
C0303	332962	KO-EL 470.000MF 25V	1	cap electrolytic 470uF/25V
C0330	336095	KO-FOL 0.100MF 63V 5%	1	cap mylar 100nF
C0331	336095	KO-FOL 0.100MF 63V 5%	1	cap mylar 100nF
C0332	336095	KO-FOL 0.100MF 63V 5%	1	cap mylar 100nF
C0333	327394	KO-FOL 5600.000PF 63V 5%	1	cap mylar 5600pF
C0334	342932	KO-FOL 0.015MF 100V 5%	1	cap mylar 15nF
C0335	342933	KO-FOL 0.022MF 100V 5%	1	cap mylar 22nF
C0336	342935	KO-FOL 0.068MF 100V 5%	1	cap mylar 68nF
C0337	327393	KO-FOL 4700.000PF 63V 5%	1	cap mylar 4700pF
C0338	342934	KO-FOL 0.033MF 100V 5%	1	cap mylar 33nF
C0401	332962	KO-EL 470.000MF 25V	1	cap electrolytic 470uF/25V
C0403	332962	KO-EL 470.000MF 25V	1	cap electrolytic 470uF/25V
C0430	342923	KO-FOL 0.220MF 63V 5%	1	cap mylar 220nF
C0431	340988	KO-FOL 0.470MF 63V 5%	1	cap mylar 470nF
C0432	342934	KO-FOL 0.033MF 100V 5%	1	cap mylar 33nF
C0435	342937	KO-FOL 1.000MF 63V 5%	1	cap mylar 1uF
C0436	344105	KO-FOL 0.027MF 100V 5%	1	cap mylar 27nF
C0437	344105	KO-FOL 0.027MF 100V 5%	1	cap mylar 27nF
C0438	344109	KO-FOL 0.056MF 63V 5%	1	cap mylar 56nF
C0501	332962	KO-EL 470.000MF 25V	1	cap electrolytic 470uF/25V
C0503	332962	KO-EL 470.000MF 25V	1	cap electrolytic 470uF/25V
C0530	336095	KO-FOL 0.100MF 63V 5%	1	cap mylar 100nF
C0531	336095	KO-FOL 0.100MF 63V 5%	1	cap mylar 100nF
C0532	336095	KO-FOL 0.100MF 63V 5%	1	cap mylar 100nF
C0533	327394	KO-FOL 5600.000PF 63V 5%	1	cap mylar 5600pF
C0534	342932	KO-FOL 0.015MF 100V 5%	1	cap mylar 15nF
C0535	342933	KO-FOL 0.022MF 100V 5%	1	cap mylar 22nF

	112619	SP 7 SYSTEM-AMP		
Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung	Menge Qty	Description
C0536	342935	KO-FOL 0.068MF 100V 5%	1	cap mylar 68nF
C0537	327393	KO-FOL 4700.000PF 63V 5%	1	cap mylar 4700pF
C0538	342934	KO-FOL 0.033MF 100V 5%	1	cap mylar 33nF
C0601	332962	KO-EL 470.000MF 25V	1	cap electrolytic 470uF/25V
C0603	332962	KO-EL 470.000MF 25V	1	cap electrolytic 470uF/25V
C0630	342923	KO-FOL 0.220MF 63V 5%	1	cap mylar 220nF
C0631	340988	KO-FOL 0.470MF 63V 5%	1	cap mylar 470nF
C0632	342934	KO-FOL 0.033MF 100V 5%	1	cap mylar 33nF
C0635	342937	KO-FOL 1.000MF 63V 5%	1	cap mylar 1uF
C0636	344105	KO-FOL 0.027MF 100V 5%	1	cap mylar 27nF
C0637	344105	KO-FOL 0.027MF 100V 5%	1	cap mylar 27nF
C0638	344109	KO-FOL 0.056MF 63V 5%	1	cap mylar 56nF
D0020	304992	DIODZ BZX 55C 6V8 0.50W	1	diode zener 6V8
D0021	304992	DIODZ BZX 55C 6V8 0.50W	1	diode zener 6V8
D0022	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0023	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0024	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0025	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0030	304992	DIODZ BZX 55C 6V8 0.50W	1	diode zener 6V8
D0031	304992	DIODZ BZX 55C 6V8 0.50W	1	diode zener 6V8
D0032	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0033	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0034	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0035	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0040	304992	DIODZ BZX 55C 6V8 0.50W	1	diode zener 6V8
D0041	304992	DIODZ BZX 55C 6V8 0.50W	1	diode zener 6V8
D0042	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0043	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0044	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0045	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0050	304992	DIODZ BZX 55C 6V8 0.50W	1	diode zener 6V8
D0051	304992	DIODZ BZX 55C 6V8 0.50W	1	diode zener 6V8
D0052	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0053	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0054	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0055	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0060	304992	DIODZ BZX 55C 6V8 0.50W	1	diode zener 6V8
D0061	304992	DIODZ BZX 55C 6V8 0.50W	1	diode zener 6V8
D0062	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0063	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0064	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0065	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0070	304992	DIODZ BZX 55C 6V8 0.50W	1	diode zener 6V8
D0071	304992	DIODZ BZX 55C 6V8 0.50W	1	diode zener 6V8
D0072	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0073	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0074	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0075	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0080	301254	DIODE 1N 4148 AXIAL	1	diode 1N 4148
D0300	304360	DIODE 1N 4007 GEGURTET	1	diode 1N 4002
D0301	341613	DIODZ BZX 55C 51V 0.50W	1	diode zener 51V 0,5watt
D0302	301310	DIODZ BZX 55C 20V 0.50W	1	diode zener 20V 0,5watt

	112619	SP 7 SYSTEM-AMP			
Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung		Menge Qty	Description
D0303	301297	DIODE BAT 85	SCHOTTKY	1	diode BAT 85
D0305	301254	DIODE 1N 4148	AXIAL	1	diode 1N 4148
D0400	304360	DIODE 1N 4007	GEGURTET	1	diode 1N 4002
D0401	341613	DIODZ BZX 55C	51V 0.50W	1	diode zener 51V 0,5watt
D0402	301310	DIODZ BZX 55C	20V 0.50W	1	diode zener 20V 0,5watt
D0403	301297	DIODE BAT 85	SCHOTTKY	1	diode BAT 85
D0405	301254	DIODE 1N 4148	AXIAL	1	diode 1N 4148
D0500	304360	DIODE 1N 4007	GEGURTET	1	diode 1N 4002
D0501	341613	DIODZ BZX 55C	51V 0.50W	1	diode zener 51V 0,5watt
D0502	301310	DIODZ BZX 55C	20V 0.50W	1	diode zener 20V 0,5watt
D0503	301297	DIODE BAT 85	SCHOTTKY	1	diode BAT 85
D0505	301254	DIODE 1N 4148	AXIAL	1	diode 1N 4148
D0600	304360	DIODE 1N 4007	GEGURTET	1	diode 1N 4002
D0601	341613	DIODZ BZX 55C	51V 0.50W	1	diode zener 51V 0,5watt
D0602	301310	DIODZ BZX 55C	20V 0.50W	1	diode zener 20V 0,5watt
D0603	301297	DIODE BAT 85	SCHOTTKY	1	diode BAT 85
D0605	301254	DIODE 1N 4148	AXIAL	1	diode 1N 4148
I0020	331340	IC TL 072 CP	2FACH OP	1	IC TL 072 CP
I0030	331340	IC TL 072 CP	2FACH OP	1	IC TL 072 CP
I0040	331340	IC TL 072 CP	2FACH OP	1	IC TL 072 CP
I0050	331340	IC TL 072 CP	2FACH OP	1	IC TL 072 CP
I0060	331340	IC TL 072 CP	2FACH OP	1	IC TL 072 CP
I0070	331340	IC TL 072 CP	2FACH OP	1	IC TL 072 CP
I0100	327197	IC NE 5532 P	2FACH OP	1	IC NE 5532 N
I0101	327197	IC NE 5532 P	2FACH OP	1	IC NE 5532 N
I0200	327197	IC NE 5532 P	2FACH OP	1	IC NE 5532 N
I0201	327197	IC NE 5532 P	2FACH OP	1	IC NE 5532 N
I0300	327197	IC NE 5532 P	2FACH OP	1	IC NE 5532 N
I0301	327197	IC NE 5532 P	2FACH OP	1	IC NE 5532 N
I0400	327197	IC NE 5532 P	2FACH OP	1	IC NE 5532 N
I0401	327197	IC NE 5532 P	2FACH OP	1	IC NE 5532 N
I0500	327197	IC NE 5532 P	2FACH OP	1	IC NE 5532 N
I0501	327197	IC NE 5532 P	2FACH OP	1	IC NE 5532 N
I0600	327197	IC NE 5532 P	2FACH OP	1	IC NE 5532 N
I0601	327197	IC NE 5532 P	2FACH OP	1	IC NE 5532 N
J003X	327779	STIFTLEISTE	3POL STL11S-1	1	connector male 3-pin
J004X	327779	STIFTLEISTE	3POL STL11S-1	1	connector male 3-pin
J005P	327779	STIFTLEISTE	3POL STL11S-1	1	connector male 3-pin
J006X	327779	STIFTLEISTE	3POL STL11S-1	1	connector male 3-pin
Q0080	307150	TRANS BC 337-25	TO 92	1	transistor BC 337-25
Q0081	307150	TRANS BC 337-25	TO 92	1	transistor BC 337-25
Q0300	307430	TRANS BC 327-25	TO 92	1	transistor BC 327-25
Q0301	307430	TRANS BC 327-25	TO 92	1	transistor BC 327-25
Q0400	307430	TRANS BC 327-25	TO 92	1	transistor BC 327-25
Q0401	307430	TRANS BC 327-25	TO 92	1	transistor BC 327-25
Q0500	307430	TRANS BC 327-25	TO 92	1	transistor BC 327-25
Q0501	307430	TRANS BC 327-25	TO 92	1	transistor BC 327-25
Q0600	307430	TRANS BC 327-25	TO 92	1	transistor BC 327-25
Q0601	307430	TRANS BC 327-25	TO 92	1	transistor BC 327-25
R0001	329215	WI-SI 10.00 OHM	0.30W 5%	1	SAFETY RESISTOR 10.0 OHM
R0002	329215	WI-SI 10.00 OHM	0.30W 5%	1	SAFETY RESISTOR 10.0 OHM
R0003	340299	WI-SI 2.20 OHM	0.30W 5%	1	safety resistor 2.20 Ohm

	112619	SP 7 SYSTEM-AMP		
Pos. Nr.	Best. Nr.		Menge	
Ref. No.	Part No.	Bezeichnung	Qty	Description
R0004	340299	WI-SI 2.20 OHM 0.30W 5%	1	safety resistor 2.20 Ohm
R0005	340299	WI-SI 2.20 OHM 0.30W 5%	1	safety resistor 2.20 Ohm
R0006	340299	WI-SI 2.20 OHM 0.30W 5%	1	safety resistor 2.20 Ohm
S00HI	351937	SCHALTER-DREH 3X4 EB.PRINT	1	switch rotary 3x4
S0300	327947	SCHALTELEMENT C42315-A1347-	1	switch element on/off
S0400	327947	SCHALTELEMENT C42315-A1347-	1	switch element on/off
S0500	327947	SCHALTELEMENT C42315-A1347-	1	switch element on/off
S0600	327947	SCHALTELEMENT C42315-A1347-	1	switch element on/off
VRLO	351946	P-DREH 2X 10KOHM LIN	1	potentiometer 2x 10k Ohm B
VR100	348430	P-DREH 10KOHM LIN	1	potentiometer 10k Ohm lin
VR200	348430	P-DREH 10KOHM LIN	1	potentiometer 10k Ohm lin
	332452	KODIERBRÜCKE 330.0101 SW	4	shorting plug