

PICTORIAL
 MODEL 370 - POWER MODULE 843032
 SCHEMATIC 1297D

Schematic Reference	DESCRIPTION	Acoustic Part No.
PCB	Printed Circuit Board	
Q 301	Transistor, PNP, 2N4248	170019
Q 302	Transistor, PNP, 2N4248	480032
Q 303	Transistor, NPN, 40408	480003
Q 304	Transistor, NPN, 2N2484 or MPSA09	480023
Q 305	Transistor, NPN, 40409	480006
Q 306	Transistor, NPN, 2N3055	480015
Q 307	Transistor, NPN, 2N3055	480015
Q 308	Transistor, NPN, 2N3055	480015
Q 309	Transistor, NPN, 2N3055	480015
Q 310	Transistor, PNP, 40410	480007
Q 311	Transistor, NPN, 2N3055	480015
Q 312	Transistor, NPN, 2N3055	480015
Q 313	Transistor, NPN, 2N3055	480015
Q 314	Transistor, NPN, 2N3055	480015
Q 315	Field Effect Transistor, P-Channel, 2N4360	480033
Q 316	Transistor, NPN, 2N2484 or MPSA09	480023
L 301	Choke, 2MHV	180008
C 301	Capacitor, 1mf, Tantalum, 35V	154004
C 302	Capacitor, 330pf, Disc, 1KV	151005
C 303	Capacitor, 1mf, Mylar, 100V	152015
C 304	Capacitor, 100mf, Electrolytic, 50V	153006
C 305	Capacitor, 10mf, Electrolytic, 50V	153002
C 306	Capacitor, 2.2mf, Tantalum, 35V	154005
C 307	Capacitor, 10mf, Electrolytic, 50V	153002
C 308	Capacitor, 24pf, Disc, 1KV	151001
C 309	Capacitor, .001mf, Disc, 1KV	151010
C 311	Capacitor, .002, Disc, 1KV	151010
C 312	Capacitor, .002, Disc, 1KV	152015
C 313	Capacitor, 1mf, Mylar, 100V	151012
C 314	Capacitor, .005mf, Disc, 1KV	154006
C 315	Capacitor, 6.5mf, Tantalum, 35V	490005
CR301	Diode, 1N914	480005
CR302	Diode, 1N914	480005
CR303	Diode, 1N914	480005
CR304	Diode, 1N914	480005
CR305	Diode, 1N914	480005
CR306	Diode, 1N914	480005
CR307	Diode, 1N914	480005
CR308	Diode, 1N914 CR 1N6229	480036
CR309	Diode, 1N6533	480028
CR310	Diode, 1N914	480005
CR311	Diode, 1N914	476327
R 301	Resistor, 27K ohm, 1/2 watt	476327
R 302	Resistor, 33K ohm, 1/2 watt	476333
R 303	Resistor, 150K ohm, 1/2 watt	476418
R 304	Tripot, 100K ohm, Klinear	475009
R 305	Resistor, 100K ohm, 1/2 watt	476410

Schematic Reference	DESCRIPTION	Acoustic Part No.
R 306	Resistor, 2.2K ohm, 1/2 watt	476222
R 307	Resistor, 6.8K ohm, 1/2 watt	476268
R 308	Resistor, 2.2K ohm, 1/2 watt	476222
R 309	Resistor, 56K ohm, 1/2 watt	476356
R 310	Resistor, 100K ohm, 1/2 watt	476410
R 311	Resistor, 1K ohm, 1/2 watt	476210
R 312	Resistor, 100K ohm, 1/2 watt	476410
R 313	Resistor, 4.7K ohm, 1/2 watt	476247
R 314	Resistor, 270K ohm, 1/2 watt	476627
R 315	Resistor, 4.7K ohm, 1/2 watt	476247
R 316	Resistor, 3.3K ohm, 1/2 watt	476233
R 317	Resistor, 3.3K ohm, 1/2 watt	476233
R 318	Resistor, 1.5K ohm, 1/2 watt	476215
R 319	Resistor, 680 ohm, 1/2 watt	476168
R 320	Resistor, 100 ohm, 1/2 watt	476110
R 321	Resistor, 1 ohm, 1/2 watt	478001
R 322	Resistor, .1 ohm, 10 watt	468810
R 323	Resistor, .1 ohm, 10 watt	468810
R 324	Resistor, 1 ohm, 1/2 watt	478001
R 325	Resistor, 100 ohm, 1/2 watt	476110
R 326	Resistor, 1 ohm, 1/2 watt	478001
R 327	Resistor, .05 ohm, 5 watt	467750
R 328	Resistor, 10 ohm, 2 watt	472010
R 329	Resistor, 22 ohm, 2 watt	472022
R 330	Resistor, 6.8K ohm, 1/2 watt	476568
R 331	Resistor, 1M ohm, 1/2 watt	476510
R 332	Resistor, 1M ohm, 1/2 watt	476510
R 333	Resistor, 10K ohm, 1/2 watt	476310
R 334	Resistor, 1M ohm, 1/2 watt	476510
R 335	Resistor, 27K ohm, 1/2 watt	476327
R 336	Resistor, 390 ohm, 1/2 watt	476139
R 337	Resistor, 270 ohm, 1/2 watt	476127
R 338	Resistor, 120K ohm, 1/2 watt	476412
R 339	Resistor, 100 ohm, 1/2 watt	476110
R 340	Resistor, 100 ohm, 1/2 watt	476110
R 341	Resistor, 18 ohm, 1/2 watt	476018