



- NOTES. 1. Q1 THRU Q4 2SC945A.  
 2. IC1 MPC4558C  
 3. IC2 MC14013B  
 4. IC3 MC14007B  
 5. IC4 MC14011B  
 6. D1 TLRG-101  
 7. D2 RD-5.1EB  
 8. D3-D6, D9-D12: 1S2473.

9. IC1. Pin 4: GND, Pin 8: +B  
 IC 2 THRU IC 4. Pin 7: GND, Pin 14: +B  
 10. D7, D8 : 1N60

SE-4 OCTAVE BOX

Input Imp. 500k ohm min.  
 Output level 1k ohm max.  
 Min. input level -40dBm  
 Signal/noise ratio >90dBm  
 Controls  
 Mode 1-octave up  
 Mode 2-1 octave down  
 Mode 3-2 octaves down  
 Balance-tone-level output  
 Noiseless electronic F.E.T. switch  
 (effect on/off)  
 Red (effect on) or normal signal  
 Green (effect on)  
 Input, output, AC adaptor input  
 9V battery (006P) included  
 SE-Up AC adaptor

**BIG JAM BY MULTIVOX**  
 370 Motor Parkway  
 Hauppauge, New York 11787  
 Telephone: (516) 231-7700  
 Telex: 510-227-9866

