



COPYRIGHT 1994 PEAVEY ELECTRONICS CORP. PRINTED IN U.S.A.

PEAVEY ELECTRONICS CORP. 711 A STREET MERIDIAN, MISSISSIPPI 39301			
TITLE	CLASSIC 30		
SIZE	CODE	NUMBER	REV
C		B1501580	
PRINT DATE	24-MAR-94	SHEET 1 OF 1	

NAME	VALUE	NUMBER	DESCRIPTION
C1	470PF	70340058	470PF 10% 50V TUB CER T&R
C10	39PF	70340052	39PF 50V TUB CER T&R
C11	047	70340017	047 MFD 10% 50V MON T&R
C12	22A25	70320012	22 MFD 25VDC LYT. CAP T&R
C13	47A50L	70340063	47 @ 50V LOW LEAKAGE
C14	270PF	70340057	270PF 10% 50V TUB CER T&R
C15	22A25	70320012	22 MFD 25VDC LYT. CAP T&R
C16	015	70340010	015 MFD 10% 50V T/C T&R
C17	22A25	70320012	22 MFD 25VDC LYT. CAP T&R
C18	022	70340012	022 MFD 10% 50V MON T&R
C19	022	70340012	022 MFD 10% 50V MON T&R
C2	001R630	70320160	001MFD 5%—630V—MT R/W
C20	1	70340100	1 MFD .80-20LV AX LP T&R
C21	001	70340000	001 MFD 10% 50V MON T&R
C22	1P10	70340101	1 MFD 50 VDC 10% MON T&R
C23	2.2A35	70320200	2.2MFD 35VDC LY CAP T&R
C24	1P10	70340101	1 MFD 50 VDC 10% MON T&R
C25	100PF	70340054	100PF 10% 50V TUB CER T&R
C26	0022	70340004	0022 MFD 10% 50V T/C T&R
C27	22R100M	70330007	22MFD 100VDC 5% MYLAR
C28	22A25	70320012	22 MFD 25VDC LYT. CAP T&R
C29	22A25	70320012	22 MFD 25VDC LYT. CAP T&R
C3	047A400	70320105	047 MFD 400 V T&R CAP
C30	22A25	70320012	22 MFD 25VDC LYT. CAP T&R
C31	1R250MY	70320096	1 MFD 250 VDC MYLAR CA BR
C32	022R400	70320106	022 MFD 400 V CAP
C33	1R250MY	70320096	1 MFD 250 VDC MYLAR CA BR
C34	22A25	70320012	22 MFD 25VDC LYT. CAP T&R
C35	022R400	70320106	022 MFD 400 V CAP
C36	22A25	70320012	22 MFD 25VDC LYT. CAP T&R
C37	0047	70340007	0047 MFD 10% 50V MON T&R
C38	01CER	70320099	01MFD 1000VDC CD-UNCUT
C39	47A500	70320005	47MF—10%—500VDC-EL-AX
C4	470PF	70340058	470PF 10% 50V TUB CER T&R
C40	47A500	70320005	47MF—10%—500VDC-EL-AX
C41	22A450	70320020	22 MFD 450 VDC LYTIC CAP
C42	22A450	70320020	22 MFD 450 VDC LYTIC CAP
C43	22A450	70320020	22 MFD 450 VDC LYTIC CAP
C44	22A25	70320012	22 MFD 25VDC LYT. CAP T&R
C45	2200A50	70320036	2200 MFD 50 VDC LYTIC CAP
C46	2200A50	70320036	2200 MFD 50 VDC LYTIC CAP
C47	10A50	70320112	10 MFD 50 V T&R
C48	100A25	70320014	100 MFD 25 VDC LYTIC CAP
C49	047P80	70340016	047MFD+80-20 50V MON T&R
C5	022R400	70320106	022 MFD 400 V CAP
C50	015	70340010	015 MFD 10% 50V T/C T&R
C51	01CER	70320099	01MFD 1000VDC CD-UNCUT
C52	0015	70340002	0015 MFD 10% 50V T/C T&R
C53	1P10	70340101	1 MFD 50 VDC 10% MON T&R
C54	1P10	70340101	1 MFD 50 VDC 10% MON T&R
C55	10A50	70320112	10 MFD 50 V T&R
C56	1P10	70340101	1 MFD 50 VDC 10% MON T&R
C6	047A400	70320105	047 MFD 400 V T&R CAP
C7	470PF	70340058	470PF 10% 50V TUB CER T&R
C8	1R250MY	70320096	1 MFD 250 VDC MYLAR CA BR
C9	001	70340000	001 MFD 10% 50V MON T&R
CR1	1N757	70400757	1N757A 9.1V 5% ZENER T&R
CR10	1N4007	70460007	1N4007 1KV.1A SIL. DIODE
CR11	1N4003	70464003	1N4003 200V SILICON DIODE
CR12	1N4003	70464003	1N4003 200V SILICON DIODE
CR13	1N4003	70464003	1N4003 200V SILICON DIODE
CR14	1N4003	70464003	1N4003 200V SILICON DIODE
CR2	1N757	70400757	1N757A 9.1V 5% ZENER T&R
CR3	1N4148	70464148	1N4148 75V 10MA SILICON DIODE
CR4	SR2873	70402873	SR-2873 2KV.250MA SIL DIO
CR5	1N4148	70464148	1N4148 75V 10MA SILICON DIODE
CR6	SR2873	70402873	SR-2873 2KV.250MA SIL DIO
CR7	1N4007	70460007	1N4007 1KV.1A SIL. DIODE
CR8	1N4007	70460007	1N4007 1KV.1A SIL. DIODE
CR9	1N4007	70460007	1N4007 1KV.1A SIL. DIODE
F2	1AFB	70900085	FUSE AGC 1
F3	10AFB	70900370	ABC 10 AMP FUSE 250V
J1	HIDMNI	71466214	2 TIP HID JACK NINS W/SPD
J2	HIDMNI	71466214	2 TIP HID JACK NINS W/SPD
J3	HIDSNI	71466217	STEREO HID JACK NINS W/SP
J4	HIDMNI	71466214	2 TIP HID JACK NINS W/SPD
J5	HIDSNI	71466217	STEREO HID JACK NINS W/SP
K1	12VRELAY	71322277	DPDT RELAY 12V
Q1	J231	70400231	J-231-TO-92-N-CHAN. 40VFET
Q2	6534	70406533	MPS-6533/34 TO-92 PNP TRANS
R1	150K	70240035	150K—1/4W—5%—CF—T&R
R10	470K	70240038	470K—1/4W—5%—CF—T&R
R11	470K	70240038	470K—1/4W—5%—CF—T&R
R12	220K	70240036	220K—1/4W—5%—CF—T&R
R13	10K	70240025	10K—1/4W—5%—CF—T&R
R14	150K	70240035	150K—1/4W—5%—CF—T&R
R15	1.5K	70240018	1500—1/4W—5%—CF—T&R
R16	1.5K	70240018	1500—1/4W—5%—CF—T&R
R17	1K	70240017	1K—1/4W—5%—CF—T&R
R18	1.5K	70240018	1500—1/4W—5%—CF—T&R
R19	68K	70240032	68K—1/4W—5%—CF—T&R
R2	150K	70240035	150K—1/4W—5%—CF—T&R
R20	220K	70240036	220K—1/4W—5%—CF—T&R
R21	2.2M	70240040	2.2M—1/4W—5%—CF—T&R
R22	220K	70240036	220K—1/4W—5%—CF—T&R
R23	1M	70240039	1M—1/4W—5%—CF—T&R
R24	100K	70240034	100K—1/4W—5%—CF—T&R
R25	1K	70240017	1K—1/4W—5%—CF—T&R
R26	22K	70240029	22K—1/4W—5%—CF—T&R
R27	10K	70240025	10K—1/4W—5%—CF—T&R
R28	1M	70240039	1M—1/4W—5%—CF—T&R
R29	47K	70240031	47K—1/4W—5%—CF—T&R
R3	100K	70240034	100K—1/4W—5%—CF—T&R
R30	22K	70240029	22K—1/4W—5%—CF—T&R
R31	22K	70240029	22K—1/4W—5%—CF—T&R
R32	2.2M	70240040	2.2M—1/4W—5%—CF—T&R
R33	1.5KW1	70210007	1500—1W—5%—MO—T&R
R34	22	70240007	22—1/4W—5%—CF—T&R
R35	100	70240010	100—1/4W—5%—CF—T&R
R36	2.2K	70240020	2200—1/4W—5%—CF—T&R
R37	2.7K	70240021	2700—1/4W—5%—CF—T&R
R38	1M	70240039	1M—1/4W—5%—CF—T&R
R39	68K	70240032	68K—1/4W—5%—CF—T&R
R4	150K	70240035	150K—1/4W—5%—CF—T&R
R40	47K	70240031	47K—1/4W—5%—CF—T&R
R41	100K	70240034	100K—1/4W—5%—CF—T&R
R42	68K	70240032	68K—1/4W—5%—CF—T&R
R43	100W5	70250006	100—5W—10%—WW—AXL
R44	47K	70240031	47K—1/4W—5%—CF—T&R
R45	220K	70240036	220K—1/4W—5%—CF—T&R
R46	1.5KW1	70210007	1500—1W—5%—MO—T&R
R47	1M	70240039	1M—1/4W—5%—CF—T&R
R48	1M	70240039	1M—1/4W—5%—CF—T&R
R49	220K	70240036	220K—1/4W—5%—CF—T&R
R5	470K	70240038	470K—1/4W—5%—CF—T&R
R50	1.5K	70240018	1500—1/4W—5%—CF—T&R
R51	1.5K	70240018	1500—1/4W—5%—CF—T&R
R52	47K	70240031	47K—1/4W—5%—CF—T&R
R53	100W5	70250006	100—5W—10%—WW—AXL
R54	68K	70240032	68K—1/4W—5%—CF—T&R
R55	47K	70240031	47K—1/4W—5%—CF—T&R
R56	220K	70240036	220K—1/4W—5%—CF—T&R
R57	100K	70240034	100K—1/4W—5%—CF—T&R
R58	400W5FP	70250020	400—5W—10%—FP 67—AXL
R59	10KW1	70210018	10K—1W—5%—MO—T&R
R6	47K	70240031	47K—1/4W—5%—CF—T&R
R60	10KW1	70210018	10K—1W—5%—MO—T&R
R61	47FP	70240090	47FP—1/4W—5%—FP—T&R
R62	47FP	70240090	47FP—1/4W—5%—FP—T&R
R63	47K	70240031	47K—1/4W—5%—CF—T&R
R64	33K	70240030	33K—1/4W—5%—CF—T&R
R66	15W5	70241097	15—5W—10%—WW—AXL
R67	180	70240012	180—1/4W—5%—CF—T&R
R7	1M	70240039	1M—1/4W—5%—CF—T&R
R70	10K	70240025	10K—1/4W—5%—CF—T&R
R71	3W5	70250041	3—5W—10%—WW—AXL
R72	3W5	70250041	3—5W—10%—WW—AXL
R73	10K	70240025	10K—1/4W—5%—CF—T&R
R74	10K	70240025	10K—1/4W—5%—CF—T&R
R8	680K	70240065	680K—1/4W—5%—CF—T&R
R9	2.2M	70240040	2.2M—1/4W—5%—CF—T&R
S1	SUZPP	71322251	SUZ P/P SWITCH PC MOUNT
S2	SUZPP	71322251	SUZ P/P SWITCH PC MOUNT
U1	4558	70404558	RC-4558 P DUAL BI-PKG 10
V1	12AX7	70806612	12 AX7/ECC 83 TUBE
V2	12AX7	70806612	12 AX7/ECC 83 TUBE
V3	12AX7	70806612	12 AX7/ECC 83 TUBE
V4	EL84	70806623	EL-84 TUBE
V5	EL84	70806623	EL-84 TUBE
V6	EL84	70806623	EL-84 TUBE
V7	EL84	70806623	EL-84 TUBE
VR1	POT0339	71190339	250KA 20% MET SPDR 1MM
VR2	1MAMSP5	71190313	1 MEG 45% MET SPIDER
VR3	POT0337	71190337	10KA 20% MET SPDR 1MM
VR4	POT0336	71190336	10K LIN MET SPIDER 1MM
VR5	1MAMSP5	71190313	1 MEG 45% MET SPIDER
VR6	20KSMS	71190326	20K S TAP MET SPIDER
VR7	POT0334	71190334	250K LIN METRIC SPDR 1MM

