



KENSINGTON

BASS

V124 - V1241

SERVICE INFORMATION

Thomas Organ Company • National Service Department • Sepulveda, California

REPLACEMENT PARTS LIST

Location	Part No.	Description
C1	24-8423-1	.1 uF 100V 10%
C2	15-18011	18 pF 500V 10%
C3	18-5053-0	10 uF 15V (Electro.)
C4	20-8529-1	.33 uF 100V 10%
C5	20-8408-1	.0056 uF 100V 10%
C6	18-5123-3	2 uF 15V (N.P. Electro.)
C7-C10	20-5002-0	.05 uF 100V 20%
C8-C11	18-5057-3	1 uF 15V (N.P. Electro.)
C9	20-8431-1	.47 uF 100V 10%
C12	20-8418-1	.039 uF 100V 10%
C13	20-8427-1	.22 uF 100V 10%
C14	18-5121-3	200 uF 6V (Electro.)
C15	18-5056-3	4 uF 15V (N.P. Electro.)
C16	18-5098-3	250 uF 12V (Electro.)
C17	20-8417-1	.033 uF 100V 10%
C18	18-5111-3	500 uF 25V (Electro.)
C19	15-18111	180 pF 500V 10%
C20	20-8602-1	.68 uF 75V 10%
C21	20-8601-1	.068 uF 75V 10%
C22	18-5114-3	25 uF 25V (Electro.)
C23	20-5317-1	.047 uF 600V 10%
C24	18-5143-3	2500 uF 35V (Electro.)
C25-C26	18-5144-3	250 uF 35V (Electro.)

RESISTORS: All 1/2W 10% Unless Otherwise Indicated

R1-R2	60-68301	68 k Ohm
R3-R4-R31	60-10401	100 k Ohm
R5-R35	60-33301	33 k Ohm
R6	60-22301	22 k Ohm
R7	60-10201	1 k Ohm
R8-R28	60-10101	100 Ohm
R9-R21-R30	60-33101	330 Ohm
R10-R16	60-47201	4.7 k Ohm
R11	24-5227-3	5 k Ohm Pot. (Tone X)
R12-R32*	60-33201	3.3 k Ohm
R13	24-5228-3	10 k Ohm Pot. (Volume)
R14-R17	60-47101	470 Ohm
R15	60-68401	680 k Ohm
R18	60-39201	3.9 k Ohm
R19	60-68201	6.8 k Ohm
R20	60-56101	560 Ohm
R22-R24	60-33901	3.3 Ohm