



Re: Silvertone 1484 reverb

« Reply #6 on: October 10, 2010, 10:17:37 am »

Silvertone Spring Reverb tank mod:

Use a short 3-spring reverb with 800 ohms input: 8EB2C1B.

First build a tank driver:

Re-wire the reverb driver tube as a follower: remove connections to Pin 2 and wire Pin 2 to Pin 7. Connect one end of a 1.5uf 250V cap to the cathodes. the other end goes to the reverb tank input.

Now fix the reverb recovery circuit: Jumper the 560K resistor and remove the resistor (and sometimes capacitor) that connect to Pin 2 of the reverb recovery tube. Reason is, these parts make a voltage divider that kills the signal. Install a 220K resistor from Pin 2 to ground as was done in AB763.

Works great!

