



output  
8.25V  
about 8 watts

RESISTANCE READINGS

Item	Tube	Pin 1	Pin 2	Pin 3	Pin 4	Pin 5	Pin 6	Pin 7	Pin 8	Pin 9
V 1	12AX7	0Ω	0Ω	0Ω	100	100	110KΩ	47KΩ	2.3KΩ	1.1Ω
V 2	6SL7	0Ω	132KΩ	2.2KΩ	25KΩ	120KΩ	2.2KΩ	1.1Ω	10Ω	10Ω
V 3	6V6GT	0Ω	100KΩ	132KΩ	47KΩ	150KΩ	2.2KΩ	1.1Ω	10Ω	10Ω
V 4	5Y3GT	0Ω	10Ω	115Ω	12.7KΩ	20KΩ	Inf.	1.1Ω	200Ω	200Ω
V 5	6V6GT	0Ω	40Ω	115Ω	12.7KΩ	20KΩ	100KΩ	1.1Ω	200Ω	200Ω
V 6	5Y3GT	Inf.	100Ω	Inf.	100Ω	Inf.	100Ω	Inf.	100Ω	100Ω

↑ MEASURED FROM PIN 3 OF V5  
↑ MEASURED FROM PIN 2 OF V6

THE COOPERATION OF THE MANUFACTURER OF THIS EQUIPMENT MAKES IT POSSIBLE TO BRING YOU THIS SERVICE