

VALVE VOLTAGE CHART

AMP MODEL: RED BEAR CUB COMBO

OUTPUT WATTAGE: 50

| | VALVE TYPE | PIN #1 | PIN #2 | PIN #3 | PIN #4 | PIN #5 | PIN #6 | PIN #7 | PIN #8 | PIN #9 |
|---|------------|--------|--------|--------|--------|--------|--------|--------|--------|--------|
| 1 | 6N2P-EB | 193 | 0 | 1.7 | H | H | 207 | 0 | 2.13 | 0 |
| 2 | 6N2P-EB | 263 | 148 | 149 | H | H | 208 | 0 | 2.13 | 0 |
| 3 | 6N2P-EB | 193 | 0 | 1.6 | H | H | 264 | 18.5 | 48.6 | 0 |
| 4 | 6N2P-EB | 277 | 105 | 160 | H | H | 272 | 111 | 160 | 0 |
| 5 | 5881 | 0 | H | 429 | 430 | -43 | 0 | H | 0 | |
| 6 | 5881 | 0 | H | 429 | 430 | -43 | 0 | H | 0 | |

Note: All voltages measured to ground under no signal condition.