

INDENTED PARTS LIST BT100Ca

Printed at SLM Electronics

LEVEL	PART NO.	DESCRIPTION	DESCRIPTION2	QUANTITY	UM	MB
0----	BT100Ca	100W 1X15" BASS COMBO	DOMESTIC VERSION	0.00	EA	M
-1---	08-619-01	BT100 COVERED CABINET		1.00	EA	M
--2--	02-450-01	CABINET COVERING GLUE	500 LBS PER DRUM	1.44	LB	B
--2--	04-703-001	BT100 RAW CAB ASSY		1.00	EA	M
---3-	04-703-010	BT100, PANEL BAFFLE		1.00	EA	M
---4-	55-275-01	3/4" 7-PLY MARINETECH	SOLIDCORE PLY END-LO	2.49	FT	B
---3-	04-703-100	BT100, PANEL TOP		1.00	EA	M
---4-	55-175-01	3/4" IND. PARTICLE BD.	BREAK 1/2UNITS ENDLO	2.26	FT	B
---3-	04-703-200	BT100, PANEL SIDE		2.00	EA	M
---4-	55-175-01	3/4" IND. PARTICLE BD.	BREAK 1/2UNITS ENDLO	2.45	FT	B
---3-	04-703-300	BT100, BOTTOM BRD		1.00	EA	M
---4-	55-175-01	3/4" IND. PARTICLE BD.	BREAK 1/2UNITS ENDLO	2.26	FT	B
---3-	04-703-700	BT100, PANEL BACK BRD		1.00	EA	M
---4-	55-175-01	3/4" IND. PARTICLE BD.	BREAK 1/2UNITS ENDLO	2.45	FT	B
---3-	04-703-800	BT100, PANEL TRAY BRD		1.00	EA	M
---4-	55-175-01	3/4" IND. PARTICLE BD.	BREAK 1/2UNITS ENDLO	1.92	FT	B
---3-	04-703-801	BT100 BAFFLE TRAY BRD		1.00	EA	M
---4-	55-175-01	3/4" IND. PARTICLE BD.	BREAK 1/2UNITS ENDLO	0.47	FT	B
---3-	04-703-900	BT100 TOP SIDE CLEAT		2.00	EA	M
---4-	55-175-01	3/4" IND. PARTICLE BD.	BREAK 1/2UNITS ENDLO	0.14	FT	B
---3-	04-703-901	BT100 BOTTOM SIDE	CLEAT	2.00	EA	M
---4-	55-175-01	3/4" IND. PARTICLE BD.	BREAK 1/2UNITS ENDLO	0.04	FT	B
---3-	04-703-902	BT100 BAFFLE CLEAT		1.00	EA	M
---4-	55-377-01	1" GRADE A MDF FIBER-	BOARD 4X8 SHEETS	0.18	FT	B
--2--	26-301-01	BLK SRO		2.59	SY	B
-1---	15B148-20	2-BUTTON FOOTSWITCH		1.00	EA	B
-1---	16-361-01	BT100a CHASSIS ASSY		1.00	EA	M
--2--	07-849-01	BT100 PCB ASSEMBLY		1.00	EA	M
---3-	07-000-00	WAVE SOLDER OPERATION		1.00	EA	M
---4-	01-000-00	NS NO COST PART	DO NOT DELETE THIS R	1.00	EA	B
---3-	07-000-01	GOOP OPERATION		1.00	EA	M
---4-	01-000-00	NS NO COST PART	DO NOT DELETE THIS R	1.00	EA	B
---3-	07A849-01	BT100 PCB SUB ASSY		1.00	EA	M
---4-	06A849-02	BT100 RAW PCB	MOD ON C61 AND C62	1.00	EA	B
---4-	10A102-11	.001 MFD 100V 10% X7R	SA101C102KAA	1.00	EA	B
---4-	10A103-11	.01 MFD 100V 10% X7R	SA201C103KAA	1.00	EA	B
---4-	10A104-01	0.1 MFD 50V 10% X7R	SA305C104KAA	8.00	EA	B
---4-	10A153-01	.015 MFD 50V 10% X7R	SA105C153KAA	4.00	EA	B
---4-	10A221-11	220 PF 100V 10% NPO	SA101A221JAA	1.00	EA	B
---4-	10A222-11	.0022 MFD 100V 10% NPO	SA101C222KAA	1.00	EA	B
---4-	10A223-01	.022 MFD 50V 10% X7R	SA105C223KAA	1.00	EA	B
---4-	10A224-01	.22 MFD 50V 10% X7R	SA305C224KAA	2.00	EA	B
---4-	10A330-21	33 PF 200V 10% NPO	SA102A330JAA	2.00	EA	B
---4-	10A331-21	AI 330PF 200V 10% NPO		1.00	EA	B
---4-	10A332-01	.0033 MFD 100V 10% X7R	SA101C332KAA	2.00	EA	B
---4-	10A471-21	470 PF 200V 10% NPO	MA302A471KAA	1.00	EA	B
---4-	10A473-11	.047 MFD 100V 10% X7R	SA301C473KAA	5.00	EA	B
---4-	10A560-21	.56 PF 200V 5% NPO	SA102A560JAA	4.00	EA	B

Printed on: 7/13/2006 2:42:32 PM

CRATE BT100

©2007 LOUD Technologies Inc. All rights reserved

BT100Ca Parts List

INDENTED PARTS LIST BT100Ca

Printed at SLM Electronics

LEVEL	PART NO.	DESCRIPTION	DESCRIPTION2	QUANTITY	UM	MB
----	4	10R104-03	.1 MFD RAD POLYCAP			
----	4	10R105-01	1UF 50VDC 10%	3.00	EA	B
----	4	12R105-50	1UF 50V RADIAL TAPED	1.00	EA	B
----	4	12R105-51	1UF 50VNP RADIAL TAPED	4.00	EA	B
----	4	12R106-35	10UF 35V RADIAL TAPED	2.00	EA	B
----	4	12R106-36	10UF 35VNP RADIAL TAPE	3.00	EA	B
----	4	12R107-32	100UF 35V 8 X 11MM	1.00	EA	B
----	4	12R225-50	2.2UF 50V RADIAL TAPED	1.00	EA	B
----	4	12R225-51	2.2UF 50VNP RADIAL TAP	3.00	EA	B
----	4	12R335-51	3.3UF 50VNP RADIAL TAP	1.00	EA	B
----	4	12R476-35	47UF 35V RADIAL TAPED	2.00	EA	B
----	4	17-836-01	.250" PC TAB ON REEL	20.00	EA	B
----	4	21A146-01	1N746ARL 3.3V ZEN DIOD	2.00	EA	B
----	4	21A444-01	1N4744ARL 15V 5% 1WZEN	6.00	EA	B
----	4	21A754-01	1N754ARL 6.8V 1/2W ZEN	1.00	EA	B
----	4	21A914-01	1N914 OR 1N4148 T&R	11.00	EA	B
----	4	37-072-01	TLO-72CP IC CHIP	7.00	EA	B
----	4	37-413-01	CMOS DUAL FLIP/FLOPS	1.00	EA	B
----	4	37-532-01	NE5532 (N/P) DUALOP IC	1.00	EA	B
----	4	76-000-05	22 GA TINNED COPPER	65.00	EA	B
----	4	76-102-01	1K OHM 1/4W 5% RES T&R	14.00	EA	B
----	4	76-103-01	10K OHM 1/4W 5% RES TR	9.00	EA	B
----	4	76-104-01	100K 1/4W 5% RES T&R	6.00	EA	B
----	4	76-105-01	1 MEG 1/4W 5% RES T&R	6.00	EA	B
----	4	76-152-01	1.5K 1/4W 5% RES T&R	2.00	EA	B
----	4	76-153-01	15K OHM 1/4W 5%RES T&R	2.00	EA	B
----	4	76-154-01	150K 1/4W 5% RES T&R	1.00	EA	B
----	4	76-221-01	220 OHM 1/4W 5% RES TR	7.00	EA	B
----	4	76-222-01	2.2K 5% 1/4W RES T&R	8.00	EA	B
----	4	76-223-01	22K OHM 1/4W 5% RES TR	13.00	EA	B
----	4	76-224-01	220K 1/4W 5% RES T&R	2.00	EA	B
----	4	76-271-01	270 OHM 1/4W 5% RES TR	2.00	EA	B
----	4	76-333-01	33K OHM 1/4W 5% RES TR	2.00	EA	B
----	4	76-470-01	47 OHM 1/4W 5% RES T&R	5.00	EA	B
----	4	76-471-01	470 OHM 1/4W 5% RES TR	2.00	EA	B
----	4	76-472-01	4.7K 1/4W 5% RES T&R	3.00	EA	B
----	4	76-473-01	47K 1/4W 5% RES T&R	6.00	EA	B
----	4	76-474-01	470K 1/4W 5% RES T&R	1.00	EA	B
----	4	76-682-01	6.8K 1/4W 5% RES T&R	4.00	EA	B
----	4	76-822-01	8.2K 1/4W 5% RES T&R	1.00	EA	B
----	4	77-102-01	1K 1/2W 5% RES T&R	1.00	EA	B
----	4	77-152-01	1.5K 1/2W 5% RES T&R	1.00	EA	B
----	4	77-222-01	2.2K 1/2W 5% RES T&R	1.00	EA	B
----	4	77-472-01	4.7K 1/2W 5% RES T&R	2.00	EA	B
----	4	78A033-01	3.3OHM 5% 1WATT MET OX	1.00	EA	B
----	4	78A821-01	820 OHM 1W 5% T&R	1.00	EA	B
----	4	96R006-01	MPS-A06	1.00	EA	B
----	4	96R013-01	MPS-A13	3.00	EA	B

Printed on: 7/13/2006 2:42:32 PM

INDENTED PARTS LIST BT100Ca

Printed at SLM Electronics

LEVEL	PART NO.	DESCRIPTION	DESCRIPTION2	QUANTITY	UM	MB
----	4	96R112-01	J112 FET	1.00	EA	B
----	4	96R175-01	J175 FET TO-92	6.00	EA	B
----	4	96R510-01	2N5210 NPN TO-92	1.00	EA	B
----	4	96R588-01	2N5088 TO-92	3.00	EA	B
----	3	10-332-01	.0033 DISC 20% UL VDE	2.00	EA	B
----	3	12-107-32	100 MFD 35V EL RAD BUL	2.00	EA	B
----	3	12-226-81	22 MFD 50V NP RAD BULK	2.00	EA	B
----	3	12-478-52	4700/50V SNAPIN RADIAL	2.00	EA	B
----	3	17-105-03	3 PIN .1" ST POL LOCK	1.00	EA	B
----	3	17-309-08	MPSS156-8-C HEADER	1.00	EA	B
----	3	17-311-08	MFAS156-8-T R.A. HDR	1.00	EA	B
----	3	21-206-01	KBPC-602 BRIDGE RECTIF	1.00	EA	B
----	3	21-222-01	YELLOW RT ANGLE LED	1.00	EA	B
----	3	21-224-01	RED LED RIGHT ANGLE	1.00	EA	B
----	3	21-227-01	GREEN RT ANGLE LED	1.00	EA	B
----	3	23-309-01	2-1/2A 3AG NORM BLO	1.00	EA	B
----	3	23-926-02	Universal Fuse Clip	2.00	EA	B
----	3	39-116-01	CLIFF S2-BNB-BLK/PC/A	4.00	EA	B
----	3	39-117-01	CLIFF S2-BBB-BLK/PC/A	2.00	EA	B
----	3	39-121-05	DUAL RCA HORIZ MOUNT	1.00	EA	B
----	3	39-308-01	XLR MALE R.A. PC MT	1.00	EA	B
----	3	66-100-01	VTL-5C7 VACTROL	1.00	EA	B
----	3	70-103-77	10KL METAL SHAFT W/NUT	4.00	EA	B
----	3	70-254-77	250KL METALSHAFT W/NUT	1.00	EA	B
----	3	70-503-77	50KL METAL SHAFT W/NUT	6.00	EA	B
----	3	71-501-02	500 OHM TRIMPOT HORIZ.	1.00	EA	B
----	3	78-001-03	.1 OHM 3W 5% RESISTOR	1.00	EA	B
----	3	78-221-05	220 OHM 5WA 5% W/FEET	2.00	EA	B
----	3	88-301-02	DPDT SWITCH W/O BUTTON	1.00	EA	B
----	3	88-303-02	LTPB 2UEE/4UEE NO CAP	2.00	EA	B
----	3	96-014-01	IRFP140 N-CHAN MOSFET	1.00	EA	B
----	3	96-340-01	2N3440 NPN TRANSISTOR	1.00	EA	B
----	3	96-515-01	2N5415 PNP TRANSISTOR	1.00	EA	B
----	3	96-914-01	IRFP9140 P-CHAN MOSFET	1.00	EA	B
----	3	99-195-05	5-PIN 250MM .1" RIBBON	1.00	EA	B
----	3	99-195-27	7 PIN 205mm CABLE	1.00	EA	B
--2--	15-501-01	BT100 SCREENED CHASSIS	MOLEX #A-28100-0628	1.00	EA	B
--2--	30-301-01	CLIFF JACK N/C NUTSET		1.00	EA	B
--2--	30-440-08	#4 X 1/4 IN PLASTITE		6.00	EA	B
--2--	30-631-01	#6 INT LOCKW. ZINC PLT	PPH TFS BLACK ZINC	3.00	EA	B
--2--	30-638-52	6-32 X 3/8 PPH TFS W/		1.00	EA	B
--2--	30-638-53	6-32X3/8" PPH MS SEMS	INT LW SEMS BLK ZINC	2.00	EA	B
--2--	30-639-52	6-32 X 9/16 PPH MS W/	W/INT LOCKW. BLK ZIN	1.00	EA	B
--2--	30-650-53	6-32 X 1/2 PPH MS	INT LW SEMS ZINC	2.00	EA	B
--2--	30-700-01	6-32 HEX KEPNUT ASSY	INT SEMS ZINC	5.00	EA	B
--2--	30-775-01	M7 X .75 DC HEX NUT	ST. W/ZINC PLATE	3.00	EA	B
--2--	30-827-01	#8-32 NUT RETAINER	9.0 X 2.0	11.00	EA	B
--2--	30-834-01	8-32 HEX KEPNUT ASSY	ZINC PLATE	4.00	EA	B

Printed on: 7/13/2006 2:42:32 PM

CRATE

©2007 LOUD Technologies Inc. All rights reserved

BT100Ca Parts List

INDENTED PARTS LIST BT100Ca

Printed at SLM Electronics

LEVEL	PART NO.	DESCRIPTION	DESCRIPTION2	QUANTITY	UM	MB
--2--	30-835-01	8 SAE FLATWASH ZINC	ID AFI STANDARD .188	6.00	EA	B
--2--	35-575-02	BERGQUIST K10-104 INS		2.00	EA	B
--2--	45-224-51	RECT BLK PUSH BUTTON	E-SWITCH #TAD	5.00	EA	B
--2--	45-754-01	BT SERIES GREEN KNOB	W/ SKIRT PANTONE 342	11.00	EA	B
--2--	47-000-02	1/2" SQ.INTER.GRND LAB		1.00	EA	B
--2--	51-232-01	BX-100 XISTOR BRACKET		1.00	EA	B
--2--	68-001-01	4" CABLE TIE 18LBS	BUNDLE -1/16"-7/8"	2.00	EA	B
--2--	85-005-01	BLACK STRAIN RELIEF		1.00	EA	B
--2--	85-056-01	1 5/16 X 6-32 HEX ALUM	SPACER	2.00	EA	B
--2--	85-062-01	1/4" PLASTIC SPACER		2.00	EA	B
--2--	85-100-01	BLACK STRAIN RELIEF		1.00	EA	B
--2--	88-212-01	10AMP SMALL AC SWITCH	SR 6N3-4	1.00	EA	B
--2--	94-291-02	94-291-01 REVERS MOUNT	WITH "I" MARKING	1.00	EA	B
--2--	97-131-08	8 X 8 X 9" HARNESS		1.00	EA	M
--3--	17-300-08	CE156-F-20-8T PIN CON.		2.00	EA	B
--3--	98-209-01	20GA BLUE UL1007 WIRE	5K FT MAX. REEL QTY	72.00	IN	B
--2--	97-152-21	14" 18GA .250/.250 RED		1.00	EA	M
--3--	17-250-02	.250" FULLY INS FASTON	.250 X .032 REELED	2.00	EA	B
--3--	98-182-02	18 GA RED UL1007 WIRE	5K FT MAX. REEL QTY	14.00	IN	B
--2--	97-153-81	8" .187/.250,18GA,BLK		2.00	EA	M
--3--	17-187-01	.187" FULL INS FASTON	.187 X .032 REELED	1.00	EA	B
--3--	17-250-02	.250" FULLY INS FASTON	.250 X .032 REELED	1.00	EA	B
--3--	98-181-01	18 GA BLACK UL1007WIRE	5K FT MAX. REEL QTY	8.00	IN	B
--2--	97-157-01	32".205/.250 BLK WIRE		1.00	EA	M
--3--	17-205-02	.205 X.020 TIN FASTON	22-18ga EXPANDED SLE	1.00	EA	B
--3--	17-250-02	.250" FULLY INS FASTON	.250 X .032 REELED	1.00	EA	B
--3--	98-206-01	20 GA BLACK UL1007WIRE	5K FT MAX. REEL QTY	32.00	IN	B
--2--	97-157-02	32".205/.250 RED WIRE		1.00	EA	M
--3--	17-205-02	.205 X.020 TIN FASTON	22-18ga EXPANDED SLE	1.00	EA	B
--3--	17-250-02	.250" FULLY INS FASTON	.250 X .032 REELED	1.00	EA	B
--3--	98-202-01	20 GA RED UL1007 WIRE	5K FT MAX. REEL QTY	32.00	IN	B
--2--	99-079-01	9' AC CORD ASSY		1.00	EA	B
-1--	18-653-70	BT100 POP BOX		1.00	EA	B
-1--	18-866-06	BT100 SHIP CARTON		1.00	EA	B
-1--	30-612-01	6-18 X 1/2" PPH "A"/T/S	BLACK ZINC	2.00	EA	B
-1--	30-819-10	#9-10 X 1"PPH LO ROOT	#10 HEAD BLACK ZINC	8.00	EA	B
-1--	30-819-51	#8 X 1-3/4 PH OVAL	LO ROOT BLACK ZINC	4.00	EA	B
-1--	30-819-53	#9 w/#10 Head x 1 1/8	Low Root Black Zinc	4.00	EA	B
-1--	30-830-21	#8-32 X 1-1/2 PH OVAL	MS BLACK ZINC	6.00	EA	B
-1--	30-832-01	#8-32 TNUT 1/4"LEB 3PRG	.209BRDIA.ZINC23/32D	2.00	EA	B
-1--	30-835-71	#8 FLANGED S/STEEL	FINISH WASHER BLK ZI	8.00	EA	B
-1--	30-838-02	8 X 3/4 PH PAN SPECIAL	LEAD SMS TWNFST BLK	16.00	EA	B
-1--	47-078-01	GENERIC LTD WAR CARD		1.00	EA	B
-1--	47-350-02	SERIAL NUMBER LABEL		1.00	EA	B
-1--	47-350-03	SHIP CARTON LABEL		1.00	EA	B
-1--	47-602-01	CRATE-GENERIC HANG TAG		1.00	EA	B
-1--	47-673-01	BT100C OWNERS MANUAL		1.00	EA	B
-1--	47-884-01	BT100 AMP TOPPER		1.00	EA	B

Printed on: 7/13/2006 2:42:32 PM

CRATE

BT100

©2007 LOUD Technologies Inc. All rights reserved

BT100Ca Parts List

INDENTED PARTS LIST BT100Ca

Printed at SLM Electronics

LEVEL	PART NO.	DESCRIPTION	DESCRIPTION2	QUANTITY	UM	MB
-1----	47-906-03	FOOTSWITCH ENCLOSED	LABEL	1.00	EA	B
-1----	51-111-01	PENN 9" STRAP HANDLE	BLACK W/ STEEL INSER	1.00	EA	B
-1----	51-111-02	PENN BLACK PLASTIC	HANDLE ENDS	2.00	EA	B
-1----	51-674-01	BT100 HEX METAL GRILL		1.00	EA	B
-1----	64-559-01	UNIVERSAL SHIPPING PAD	ARCEL MATERIAL	8.00	EA	B
-1----	68-058-01	LOGO		1.00	EA	B
-1----	68-548-01	LRG FRNT CRNR		4.00	EA	B
-1----	68-548-51	LRG REAR CRNR		4.00	EA	B
-1----	68-705-01	42X50 1 MIL HD POLYBAG		1.00	EA	B
-1----	79-001-01	TUNER MODULE	160 PER ROLL CLEAR B	1.00	EA	B
-1----	81-203-01	BLACK RECESS BUMPER	VPF00427	4.00	EA	B
-1----	86-118-14	15" , 40HM, 150W	2.5"VC, 54.7 OZ MAG	1.00	EA	B

Printed on: 7/13/2006 2:42:32 PM

CRATE

BT100

©2007 LOUD Technologies Inc. All rights reserved

BT100Ca Parts List