# CARVERaudio.com

A Website Devoted to the Legacy of Bob Carver's Electronics

This, and all manuals found on CARVERaudio.com have been painstakingly scanned, compiled, cataloged and archived by our <u>dedicated forum members</u>, for the benefit of all Carver audio fanatics. These manuals are NOT intended for re-sale. If you should find these manuals "For Sale" on any website, please report your findings to us, so we may have them removed.


# CARVERaudio.com


CARVER

TFM-35x

SCHEMATICS AND LAYOUTS

Please report any sales of this manual to our forum @ www.CARVERaudio.com








Please report any sales of this manual to our forum @ www.CARVERaudio.com


This manual is provided free, courtesy of CARVERaudio.com WIR35X ğ 9 § \_\_\_\_ W12 RED 18 AWG WII BRN 18 AMG WIB RED 18 AWG WIO YEL 18 AWG A1 602-00593-01 -0 § 606-00640-04 (230V CONV) 606-00640-05 (EURO) W11 BRN W9 BRN W10 YEL 550-10059-01 WI7 WID IS AWG WHT 18702 BLK 18 AWG GRAY 18 AWG (NEUTRAL) WHIT 18 AWG 550-00041-01 CN101 -Tage |-WB RED W12 RED W7 ORN W13 ORN W2 RED W3 BILU 2 5 MAY TEL (-DS ONLY) SNS SNS 7


Please report any sales of this manual to our forum @ www.CARVERaudio.com




















MFG,RE,210,2 Carver Corporation 14-DEC-1995 15:07

## BILL OF MATERIALS REPORT

PLANT CODE: CARVER

REQUESTER: ALVAREZ PAGE NO: 1

# SORTED BY ASSEMBLY PART NUMBER, COMPONENT PART NUMBER AS OF 12/14/95

CLASS CODE: 5 SUB-ASSEMBLIES PART: 607-00640-03

DESC: AMP ASSY - TFM-35X 120V CONV UON: EA SC: X REV: N

COMPONENT PART/ REFERENCE INFO	DESCRIPTION	RV	ITEM NUMBR	SC		QTY PER ASSEMBLY	YIELD FACTR		-OFFSET LD FIXED VARIA		EFFECTIV DATE	INACTIVE DATE
101-30001-00	FOOT, RUBBER ROUND .63W X .31H	A	2	M	EA	2.00	1.00	0	0	0.00	05/18/94	99/99/99
105-30007-01	FOOT, 1.96 DIA X .64 HIGH	A	1	P	EA	4.00	1.00	0	0	0.00	07/18/94	99/99/99
105-40014-00	FUSEHOLDER PANEL MNT 120-230V	A	5	P	EA	1.00	1.00	0	0	0.00	00/00/00	99/99/99
105-50000-00	FUSE CARRIER 120V	A	10	P	EA	1.00	1.00	. 0	0	0.00	00/00/00	99/99/99
106-30011-01 HEATSINK MOUNTING	GRONMET, #8 ROUND HOLE	A	15	P	EA	2.00	1.00	0	0	0.00	01/17/94	99/99/99
112-20001-00	MOUNT TYRAP WHT	A	12	P	EA	3.00	1.00	0	0	0.00	01/17/94	99/99/99
112-30008-01	METER, 500W SCALE	A	240	P	EA	2.00	1.00	0	0	0.00	08/01/95	99/99/99
115-30016-01 J1,2	POST, BDG, DUAL SHORT RED/BLK	C	13	P	EA	2.00	1.00	0	0	0.00	00/00/00	99/99/99
118-90007-00 LINECORD	STRN RE MCT.063 SJT 16/3218/3	A	20	P	EA	1.00	1.00	0	0	_ 0.00	00/00/00	99/99/99
151-20002-00 MAIN CCA, MOUNTIN	SCRW, MACH PP 4-40X3/8 BLK WAX	A	36	P	EA	5.00	1.00	0	0	0.00	02/15/94	99/99/99
151-20104-00 HANDLE BRKT TO HAN	SCREW MACH PP BLK 8-32X5/8	A	55	P	EA	4.00	1.00	0	0	0.00	05/18/94	99/99/99
151-30001-00 DISPLAY CCA (2)	SCREW SHT MTL PP BLK 4X1/4 HBH	A	35	P	EA	7.00	1.00	0	0	0.00	02/15/94	99/99/99
METER BRKT (2), P		A	80	P	EA	2.00	1.00	0	0	0.00	00/00/00	99/99/99
JACKS 151-30005-01	SCREW SHT HTL PP BLK 4X3/16 B	A	85	P	EA	2.00	1.00	0	0	0.00	10/03/94	99/99/99
MONO SWITCH 151-30102-00	SCREW SHT MTL PP BLK 8X3/8 MAH	A	42	P	EA	4.00	1.00	0	0	0.00	07/18/94	99/99/99
151-30102-00	SCREW SHT MTL PP BLK 8X3/8 #A#	A	45	P	EA	2.00	1.00	0	0	0.00	02/15/94	99/99/99
HEATSINK 151-30106-00	SCREW SHT MTL PP BLK 8X3/4 MAM	A	46	P	EA	8.00	1.00	0	0	0.00	05/18/94	99/99/99
HANDLE BRKT TO FR' 151-30107-01	F PNL, XFMR SCRW, SM PP SERR BLK 6X1/4 MBM	A	40	P	EA	23.00	1.00	0	0	0.00	05/19/95	99/99/99
BACK PNL (6), TOP HEATSINK MTG (4)	_											
FRT PNL ASSY MTG ( 151-30168-03	(7) SCRW PNH #4 SLFTPG W/WSHR 1/2"	A	75	P	EA	24.00	1.00	0	0	0.00	00/00/00	99/99/99
XISTOR 151-40260-01	SCRW METRIC MACH PP 3X6	В	50	P	EA	2.00	1.00	0	0		00/00/00	
PWR SW		_		•					•			
152-20003-01 XFMR	U-TYPE CLIP #8 SHT MTL	A	95	P	EA	4.00	1.00	0	0		05/18/94	
154-30002-00 HANDLE, TRANSFORMI	WASHER, SPLIT LOCK BLK. #8	A	105	P	EA	8.00	1.00	0	0	0.00	09/15/94	99/99/99
154-40008-01	WASHER, SHOULDER NYLON, #4	A	102	P	EA	4.00	1.00	0	0	0.00	06/19/95	99/99/99
9233,234,235,236 159-50002-00	TYRAP 4"L WHT	A	115	P	EA	8.00	1.00	0	0	0.00	05/18/94	99/99/99
159-70003-02	CLAMP, CABLE KURLY-LOK .5	A	116	P	EA	1.00	1.00	0	0	0.00	01/17/94	99/99/99
CLAMP 160-20014-00	CONNECTOR, SPLICE NYLON INSUL	A	118	P	EA	1.00	1.00	0	0	0.00	01/17/94	99/99/99
SPLICE XFMR WIRES 160-20500-07	FAST NYL 16-14AWG BLU .250	С	119	P	EA	2.00	1.00	0	0	0.00	00/00/00	99/99/99
(LINECORD) 315-13006-00	FUSE, MDA 10	A	120	P	EA	1.00	1.00	0	0	0.00	00/00/00	99/99/99
F1 318-10028-01	SWITCH POWER SPST	В	125	P	EA	1.00	1.00	0	0	0.00	00/00/00	08/01/96-
s3 318-50004-00	SWITCH, THERMAL U1210005310A	C	130	P	EA	2.00	1.00	0	0	0.00	00/00/00	99/99/99
\$1,2 321-30013-00 9211,212,217,218,2 9226	XSTR TO3P(L) NPN PWR 2SC3281-0 221,222,225,	В	135	P	EA	8.00	1.00	0	0	0.00	06/19/95	99/99/99

MFG,RE,210,2 Carver Corporation 14-DEC-1995 15:07

### BILL OF MATERIALS REPORT

PLANT CODE: CARVER

\_ ===

REQUESTER: ALVAREZ PAGE NO: 2

# SORTED BY ASSEMBLY PART NUMBER, COMPONENT PART NUMBER AS OF 12/14/95

CLASS CODE: 5 SUB-ASSEMBLIES PART: 607-00640-03

DESC: AMP ASSY - TFM-35X 120V CONV UOM: EA SC: X REV: N

COMPONENT PART/ REFERENCE INFO	DESCRIPTION	RV	ITEM NUMBR	sc		QTY PER ASSEMBLY	YIELD FACTR		-OFFSET LD T		EFFECTIV DATE	INACTIVE DATE
321-30014-00 0213,214,219,220,	XSTR TO3P(L) PNP PWR 2SA1302-0 223,224,227,	В	140	P	EA	8.00	1.00	0	0	0.00	06/19/95	99/99/99
9228 321-80006-01	XISTOR CASE 340D-01 NPN TIP35C	C	142	P	EA	2.00	1.00	0	0	0.00	06/19/95	99/99/99
9233, 234 321-80007-01	XISTOR CASE 3400-01 PNP TIP36C	D	143	P	EA	2.00	1.00	0	0	0.00	06/19/95	99/99/99
9235, 236 401-10204-00	WIRE 18 AWG TEW ORANGE 9"	A	150	P	EA	1.00	1.00	0	0	0.00	00/00/00	99/99/99
W1 401-10222-00	WIRE 18 AWG TEW RED 9"	A	146	P	EA	1.00	1.00	0	0	0.00	00/00/00	99/99/99
W2 401-10225-00	WIRE 18 AWG TEW BLUE 5.25*	A	145	P	EA	2.00	1.00	0	0	0.00	00/00/00	99/99/99
W3,6 401-90023-01	LC, RND 16/2 PLZD-CSA/UL APRD	A	160	P	EA	1.00	1.00	0	0	0.00	00/00/00	99/99/99
P1 402-10007-00	TUBING HTSHRK DUAL WALL 1/2"	A	165	P	FT	0.09	1.00	0	0	0.00	02/15/94	99/99/99
FUSEHOLDER 403-00002-00	COLORED ENAMEL W&W #452	-	167	Ε	EA	0.00	1.00	0	0	0.00	09/15/94	99/99/99
APPLY TO ITEM 95 403-10020-00	LOCTITE #222	A	170	Ε	EA	0.00	1.00	0	0	0.00	03/02/95	99/99/99
403-40016-00	GASKET, FOAM .25THKX.830W (LS)	-	175	E	EA	0.00	1.00	0	0	0.00	01/17/94	99/99/99
METER BRKT 502-20105-01	CHASSIS, TFM-35X	E	185	В	EA	1.00	1.00	0	0	0.00	00/00/00	99/99/99
503-20117-01	PANEL, REAR - TFM-35X	D	191	В	EA	1.00	1.00	0	0	0.00	01/17/94	99/99/99
503-20118-01	BEZEL, POWER SWITCH	A	192	В	EA	1.00	1.00	0	0	0.00	01/17/94	99/99/99
503-20134-01	BEZEL, METER	В	205	В	EA	2.00	1.00	0	0	0.00	08/01/95	99/99/99
503-20135-01	PANEL, FRONT, TFM-35X	D	190	В	EA	1.00	1.00	0	0	0.00	08/01/95	99/99/99
504-20113-01	COVER - TFM-35X	A	195	В	EA	1.00	1.00	0	0	0.00	00/00/00	99/99/99
507-00050-00	BRACKET THERMAL SW UNIVERSAL	C	200	В	EA	2.00	1.00	0	0	0.00	00/00/00	99/99/99
(\$1,2) 507-20075-01	BRACKET, HANDLE	В	220	В	EA	2.00	1.00	0	0	0.00	00/00/00	99/99/99
507-20076-01	BRACKET, POWER SWITCH	A	225	B	EA	1.00	1.00	0	0	0.00	00/00/00	99/99/99
507-20119-01	BRACKET, METER	В	210	В	EA	1.00	1.00	0	0	0.00	08/01/95	99/99/99
508-20038-01	KNOB, DISPLAY BOARD	A	280	P	EA	2.00	1.00	0	0	0.00	00/00/00	99/99/99
508-20039-01	KNOB, POWER SWITCH	A	275	P	EA	1.00	1.00	0	0	0.00	00/00/00	99/99/99
(\$3) 509-20008-01	FERRULE, .25 DIA, BLACK	В	250	P	EA	4.00	1.00	0	0	0.00	00/00/00	99/99/99
510-20013-01	HANDLE 2.75 X .25 DIA 8-32 BLK	B	255	P	EA	2.00	1.00	0	0	0.00	00/00/00	99/99/99
511-20043-01	HEATSINK - TFM-35X	C	230	В	EA	2.00	1.00	0	0	0.00	00/00/00	99/99/99
512-10654-01	INSULATOR, 10 POSITION	A	235	B	EA	2.00	1.00	0	0	0.00	06/19/95	99/99/99
530-20029-00	LABEL, CITY OF LA APPROVED		242	P	EA	1.00	1.00	0	0	0.00	10/15/94	99/99/99
530-20100-00 ONE ON BACK OF CH INSIDE OF CHAS, C		A	245	E	RL	0.00	1.00	. 0	0	0.00	10/15/94	99/99/99
TO ITEM 242 550-00039-01	CABLE ASSY - 4 PIN #24 TR64	B	290	B	EA	1.00	1.00	0	0	0.00	00/00/00	99/99/99
W18 602-00592-01	CCA, DISPLAY	C	265	X	EA	1.00	1.00	0	0	0.00	00/00/00	99/99/99
A2												



MFG,RE,210,2 Carver Corporation 14-DEC-1995 15:07

BILL OF MATERIALS REPORT

PLANT CODE: CARVER

REQUESTER: ALVAREZ

PAGE NO:

SORTED BY ASSEMBLY PART NUMBER, COMPONENT PART NUMBER AS OF 12/14/95

CLASS CODE: 5 SUB-ASSEMBLIES PART: 607-00640-03

DESC: AMP ASSY - TFM-35X 120V CONV UOM: EA SC: X REV: N

COMPONENT PART/ REFERENCE INFO	DESCRIPTION	RV	ITEM NUMBR	sc		QTY PER ASSEMBLY	YIELD FACTR		-OFFSET FIXED V	LD TIME ARIABLE		INACTIVE DATE
602-00593-01	CCA, MAIN - TFM-35X	M	260	X	EA	1.00	1.00	0	0	0.00	00/00/00	99/99/99
A1 602-00593-03	CCA, LIGHT	8	262	X	EA	1.00	1.00	0	0	0.00	00/00/00	99/99/99
A3 602-00593-04	CCA, XSTR LEFT	A	263	X	EA	1.00	1.00	0	0	0.00	00/00/00	99/99/99
A5 602-00593-05	CCA, XSTR RIGHT	A	264	X	EA	1.00	1.00	. 0	0	0.00	00/00/00	99/99/99
A6 602-00600-01	CCA, INPUT - TFM-35X	D	261	X	EA	1.00	1.00	0	0	0.00	01/17/94	99/99/99
617-10114-01	TRANSFORMER, PUR AMP, 500W	E	285	B	EA	1.00	1.08	0	0	0.00	00/00/00	99/99/99



MFG,RE,210,2 Carver Corporation 14-DEC-1995 15:07

### BILL OF MATERIALS REPORT


PLANT CODE: CARVER REQUESTER: ALVAREZ PAGE NO: 1

# SORTED BY ASSEMBLY PART NUMBER, COMPONENT PART NUMBER AS OF 12/14/95

CLASS CODE: 5
SUB-ASSEMBLIES
PART: 602-00592-01
DESC: CCA, DISPLAY

UOM: EA SC: X REV: C

COMPONENT PART/ REFERENCE INFO	DESCRIPTION	RV	ITEM NUMBR	sc		QTY PER ASSEMBLY	YIELD FACTR			T LD TIME VARIABLE	EFFECTIV DATE	INACTIVE DATE
160-20025-04	HEADER, 4 PIN, .098 CENTER	A	10	P	EA	1.00	1.00	0	0	0.00	00/00/00	99/99/99
J2 201-00088-00	CAP CER DISC 47 PF 100V 5% GP	A	15	P	EA	2.00	1.00	0	0	0.00	00/00/00	99/99/99
C3,14 201-00092-00 C7,18	CAP CER DISC 100 PF 100V 5% GP	A	20	P	EA	2.00	1.00	0	0	0.00	00/00/00	99/99/99
201-00127-02 C11,20,21	CAP CR DSK .01UF 50V +80-20 .2	В	25	Ρ,	EA	3.00	1.00	0	0	0.00	00/00/00	99/99/99
204-00140-00 C9,10	CAP MTL FLM .033 UF 50V 5%	В	30	P	EA	2.00	1.00	0	0	0.00	01/27/94	99/99/99
205-00006-02 C8,19	CAP LYTIC 4.7UF 50V 20% RAD .2	B	35	P	EA	2.00	1.00	0	0	0.00	00/00/00	99/99/99
205-00011-02 C1,2,12,13	CAP LYTIC 22 UF 25V 20% RAD .2	D	40	P	EA	4.00	1.00	0	0	0.00	00/00/00	99/99/99
205-00013-02 C6,17	CAP LYTIC 47 UF 25V 20% RAD .2	В	45	P	EA	2.00	1.00	0	0	0.00	00/00/00	99/99/99
205-00016-02 C4,5,15,16	CAP LYTIC 100UF 25V 20% RAD .2	В	50	P	EA	4.00	1.00	0	0		00/00/00	
259-10062-11 R13,35	POT, 500K LAYDOWN PCB MOUNT	A	55	P	EA	2.00	1.00	0	0	0.00	01/27/94	99/99/99
260-50101-04D R2,24	RES, CF 5% 100 OHM 1/4W .5	A	60	P	EA	2.00	1.00	0	0	0.00	00/00/00	99/99/99
260-50102-04D R9,31	RES, CF 5% 1K 1/4W .5	A	65	P	ĘΑ	2.00	1.00	0	, 0	0.00	00/00/00	99/99/99
260-50155-04D R18,19	RES, CF 5% 1.5M 1/4W .5	A	70	P	EA	2.00	1.00	0	0	0.00	00/00/00	99/99/99
260-50180-04b R7,29	RES, CF 5% 18 OHM 1/4W .5	A	75	P	EA	2.00	1.00	0	0	0.00	00/00/00	99/99/99
260-50202-04D R6,28	RES, CF 5% 2K 1/4W .5	A	80	P	EA	2.00	1.00	0	0	0.00	00/00/00	99/99/99
260-50203-04D R5,27	RES, CF 5% 20K 1/4W .5	A	85	P	EA	2.00	1.00	0	0	0.00	00/00/00	99/99/99
260-50223-04D R16,21,22	RES, CF 5% 22K 1/4W .5	A	90	P	EA	3.00	1.00	0	0	0.00	00/00/00	99/99/99
260-50224-04D R1,23	RES, CF 5% 220K 1/4W .5	A	95	P	EA	2.00	1.00	0	0	0.00	00/00/00	99/99/99
260-50304-04D R38,39	RES, CF 5% 300K 1/4W .5	A	97	P	EA	2.00	1.00	0	0	0.00	09/15/94	99/99/99
260-50394-04D R15,37	RES, CF 5% 390K 1/4W .5	A	105	P	EA	2.00	1.00	0	0	0.00	00/00/00	99/99/99
260-50432-04D R8,30	RES, CF 5% 4.3K 1/4W .5	A	110	P	EA	2.00	1.00	0	0	0.00	00/00/00	99/99/99
260-50473-04D R3,14,25,36	RES, CF 5% 47K 1/4W .5	A	115	P	EA	4.00	1.00	0	0	0.00	11/30/93	99/99/99
260-50561-04D R4,26	RES, CF 5% 560 OHM 1/4W .5	A	120	P	EA	2.00	1.00	0	0	0.00	00/00/00	99/99/99
260-50684-04D R17,20	RES, CF 5% 680K 1/4W .5	A	125	P	EA	2.00	1.00	0	0	0.00	00/00/00	99/99/99
260-50820-04D R12,34	RES, CF 5% 82 OHM 1/4W .5	A	130	P	EA	2.00	1.00	0	0	0.00	00/00/00	99/99/99
260-50911-04D R10,11,32,33	RES, CF 5% 910 OHM 1/4W .5	A	135	P	EA	4.00	1.00	0	0	0.00	00/00/00	99/99/99
318-10029-01 \$1,2	SWITCH, PUSHBUTTON, STR, DPDT	B	140	P	EA	2.00	1.00	0	0	0.00	00/00/00	99/99/99
320-20001-00 D1,2	DIODE, 1N4148 75V .4	C	145	P	EA	2.00	1.00	0	0	0.00	00/00/00	99/99/99
321-10000-00 91,3	XISTOR 152 NPN SM SG MPSW06	A	150	P	EA	2.00	1.00	0	0	0.00	00/00/00	99/99/99
321-40010-00 Q2,4	XISTOR TO92 NPN SM SG 2N4123	A	160	P	EA	2.00	1.00	0	0	0.00	00/00/00	99/99/99
330-30028-01 U1,2	IC, DUAL OP AMP 4558 8 PIN SIP	A	165	P	ΕA	2.00	1.00	0	0	0.00	00/00/00	99/99/99
401-30002-00 W3	JUMPER INSUL .3"x.25x.25 #22	-	167	P	EA	1.00	1.00	0	8	0.00	11/30/93	99/99/99
501-00592-01	PCB, DISPLAY	C	1	В	EA	1.00	1.00	0	0	0.00	00/00/00	99/99/99



MFG,RE,210,2 Carver Corporation 14-DEC-1995 15:07

BILL OF MATERIALS REPORT

PLANT CODE: CARVER

REQUESTER: ALVAREZ PAGE NO: 2

SORTED BY ASSEMBLY PART NUMBER, COMPONENT PART NUMBER AS OF 12/14/95

CLASS CODE: 5
SUB-ASSEMBLIES
PART: 602-00592-01
DESC: CCA, DISPLAY

UON: EA SC: X REV: C

COMPONENT PART/ REFERENCE INFO	DESCRIPTION	RV	ITEM NUMBR SC		QTY PER ASSEMBLY	YIELD FACTR			T LD TIME VARIABLE	EFFECTIV DATE	INACTIVE DATE
550-00036-01	CABLE ASSY-3PIN #24 TR64 13.0"	В	170 B	EA	1.00	1.00	0	0	0.00	00/00/00	99/99/99
W2 550-00037-01	CABLE ASSY-5PIN #24 TR64 7.0M	B	175 B	EA	1.00	1.00	0	0	0.00	00/00/00	99/99/99
u1 550-00038-01	CABLE ASSY-2 PIN #24 TR64 8.5	B	5 B	EA	1.00	1.00	. 0	0	0.00	04/15/94	99/99/99



MFG,RE,210,2 Carver Corporation 14-DEC-1995 15:07

### BILL OF MATERIALS REPORT

PLANT CODE: CARVER

REQUESTER: ALVAREZ PAGE NO: 1

SORTED BY ASSEMBLY PART NUMBER, COMPONENT PART NUMBER
AS OF 12/14/95

CLASS CODE: 5 SUB-ASSEMBLIES PART: 602-00593-01

DESC: CCA, MAIN - TFM-35X

UOM: EA SC: X REV: M

COMPONENT PART/	DECOMPANYON		ITEM	er		QTY PER ASSEMBLY	YIELD FACTR			T LD TIME VARIABLE	EFFECTIV DATE	INACTIVE DATE
115-60002-01	TAB, PCB, .250	 A		 P	EA	2.00	1.00	0	0		05/09/94	99/99/99
TP701,702 119-20035-01	TEST POINT	A	10	P	EA	20.00	1.00	0	0	0.00	05/02/94	99/99/99
TP201,202,203,204 TB501 (3), TB502	,301,302,303											
TB701 (3), TB702 151-30002-00		A	20	P	EA	1.00	1.00	0	0	0.00	08/18/94	99/99/99
0451 TO H451 160-20009-00	CONNECTOR 3 PIN B-TONE CN401	A	25	P	EA	4.00	1.00	0	0	0.00	00/00/00	99/99/99
CN103,201,202,401 160-20011-00 CN451	CONNECTOR 5 PIN B-TONE CN451	A	30	P	EA	1.00	1.00	0	0	0.00	00/00/00	99/99/99
160-30045-06 CN101,102	CONN, HDR, 6 PIN .100 SHROUDED	B	40	P	EA	2.00	1.00	0	0	0.00	00/00/00	99/99/99
201-00009-00 c207,208,209,210	CAP CER DISC 68 PF 1000V 10%	В	45	<b>P</b>	EA	4.00	1.00	0	_		00/00/00	
201-00012-00 c201,202,203,204	CAP CER DISC 100 PF 1000V 10%	В	· 50		EA	4.00	1.00	0	_		00/00/00	
201-00023-00 c301,302		В	55		EA	2.00	1.00	0			08/18/94	
201-00035-00 C701	CAP, CER .01UF 250VAC UL/CSA	B	60		EA	1.00	1.00	0			00/00/00	
201-00061-00 c227,228	CAP CER DISC .001UF 250V 10XUL		65		EA	2.00	1.00	0			00/00/00	
204-00003-00 c315	CAP PLYFLM .001 UF 100V 10% RD		70	-	EA	1.00	1.00	0	•		00/00/00	
204-00015-00 C303,304,305,306,	CAP PLYFLM .01 UF 100V 10% RAD 452		75 80		EA EA	5.00 10.00	1.00	0	•		00/00/00	
204-00042-00 C215,216,217,218,	CAP PLYFLM .1 UF 100V 5% RAD 219,220	٨	au	•	EA	10.00	1.00	·	Ū	0.00	00,00,00	
C221,222,223,224 204-00065-00 C225,226	CAP PLYFLM .047 UF 100V 5% RAD	A	85	P	EA	2.00	1.00	0	0	0.00	00/00/00	99/99/99
205-00001-02 C510	CAP LYTIC 1 UF 50V 20% RAD .2	В	90	P	EA	1.00	1.00	0	0	0.00	11/27/95	99/99/99
205-00006-02 c205,206	CAP LYTIC 4.7UF 50V 20% RAD .2	B	95	P	EA	2.00	1.00	0	0	0.00	11/14/95	99/99/99
205-00011-02 c309	CAP LYTIC 22 UF 25V 20% RAD .2	D	100	P	EA	1.00	1.00	0	0	0.00	07/18/94	99/99/99
205-00013-02 C307,308,507,508,	CAP LYTIC 47 UF 25V 20% RAD .2 511.512	B	105	P	EA	6.00	1.00	0	0		11/27/95	
205-00042-00 C509	CAP LYTIC 470 UF 35V 20% RAD	В	110	P.	EA	1.00	1.00	0			00/00/00	
205-00054-02 C211,212,213,214	CAP LYTIC 1 UF 100V 20% RAD .2	В	115		EA	4.00	1.00	0			11/27/95	
205-00065-02 C311	CAP LYTIC .47UF 50V RAD .2LS		120	-		1.00		0			11/27/95	
205-00159-00 c310	CAP LYTIC 33 UF 25V 20% RAD	A	125				1.00	0			00/00/00	
205-00161-00 C501,502		В	130				1.00	0			00/00/00	
205-00177-00 C505,506	CAP, LYTIC 6800 UF, 35V	A .	135			2.00		0			00/00/00	
205-00178-00 C503,504	CAP, LYTIC 3300 UF, 63V	A	140 150			2.00	1.00	0			00/00/00	
259-30012-01 VR201,202	POT, 500 OHM 6MM ROUND	A	155		EA		1.00	0	_		00/00/00	
260-50100-04A R217,218,219,220, R227,228		A										_
260-50101-04A R273,274,285,286, R313,314,315,316	RES, CF 5% 100 OHM 1/4W 287,288	A	160	P	EA	10.00	1.00	0	0	0.00	00/00/00	<del>99</del> /99/99
260-50102-03A R501,502	RES, CF 5% 1K 1/8W	B	165	P	EA	2.00	1.00	0	0	0.00	00/00/00	99/99/99
										-		

MFG,RE,210,2 Ca 14-DEC-1995 15:07 Carver Corporation

## BILL OF MATERIALS REPORT

PLANT CODE: CARVER

REQUESTER: ALVAREZ PAGE NO:

SORTED BY ASSEMBLY PART NUMBER, COMPONENT PART NUMBER AS OF 12/14/95

CLASS CODE: SUB-ASSEMBLIES PART: 602-00593-01

DESC: CCA, MAIN - TFM-35X

UOM: EA SC: X REV: M

D	ESC: CCA, MAIN - 1	rfm-35X	UOM: EA SC:	X	KEV:									
_	OMPONENT PART/ EFERENCE INFO	DESCRIPTION		RV	ITEM NUMBR	SC		QTY PER ASSEMBLY	YIELD FACTR			T LD TIME VARIABLE	EFFECTIV DATE	INACTIVE DATE
	60-50102-04A	RES, CF 5% 1K 1/4	1	A	170	P	EA	6.00	1.00	0	0	0.00	00/00/00	99/99/99
2	R205,206,207,208,2 60-50102-07A	RES, CF 5% 1K 1W		В	175	P	EA	1.00	1.00	0	0	0.00	00/00/00	99/99/99
2	R451 60-5010 <b>3-04A</b>	RES, CF 5% 10K 1/4	iu .	A	180	P	EA	3.00	1.00	0	0	0.00	00/00/00	99/99/99
2	R213,214,503 60-50104-03A	RES, CF 5% 100K 1	/8 <b>u</b>	B	185	P	EA	1.00	1.00	0	0	0.00	00/00/00	99/99/99
	R323 60-50122-04D	RES, CF 5% 1.2K 1	/4w .5	A	190	P	EA	2.00	1.00	0	0	0.00	11/21/95	99/99/99
_	60-50132-04A	RES, CF 5% 1.3K 1	/4 <b>u</b>	A	195	P	EA	2.00	1.00	0	C	0.00	00/00/00	99/99/99
2	R289,290 60-50151-04A	RES, CF 5% 150 OH	4 1/4W	A	200	P	EA	4.00	1.00	0	0	0.00	00/00/00	99/99/99
2	R301,302,303,304 60-50152-04A	RES, CF 5% 1.5K 1,	/4 <b>u</b>	A	205	P	EA	2.00	1.00	0	0	0.00	00/00/00	99/99/99
2	R229,230 60-50183-03A	RES, CF 5% 18K 1/8	3LI	B	210	P	EA	1.00	1.00	0	0	0.00	00/00/00	99/99/99
2	R332 60-50203-03A	RES, CF 5% 20K 1/8	Bu	В	215	P	EA	1.00	1.00	0	0	0.00	00/00/00	99/99/99
2	R328 60-50221-04A	RES, CF 5% 220 OH	1 1/4W	A	220	P	EA	4.00	1.00	0	0	0.00	00/00/00	99/99/99
2	R239,240,241,242 60-50222-04A R231,232,233,234,3	RES, CF 5% 2.2K 1	/4 <b>u</b>	A	225	P	EA	8.00	1.00	8	0	0.00	00/00/00	99/99/99
	R281,282 60-50223-03A	RES, CF 5% 22K 1/8	RLJ	В	230	P	EA	1.00	1.00	0	0	0.00	00/00/00	99/99/99
	R325 60-50224-03A	RES, CF 5% 220K 1/		В			EA	1.00	1.00	0	0		00/00/00	
	R327 60-50302-04A	RES, CF 5% 3K 1/4		- A	240		EA	4.00	1.00	0	0	0.00	00/00/00	99/99/99
	R277,278,291,292 60-50333-03A	RES, CF 5% 33K 1/8	•	В	245		EA	1.00	1.00	0	0		00/00/00	
	R331 60-50393-04A	RES. CF 5% 39K 1/4		Ā	250		EA	2.00	1.00	0	0	0.00	00/00/00	99/99/99
	R317,318 60-50472-04A	RES, CF 5% 4.7K 1		A			EA	4.00	1.00	0	0		00/00/00	
	R305,306,307,308 60-50473-03A	RES, CF 5% 47K 1/8		B	260		EA	2.00	1.00	0			00/00/00	
	R324,326 60-50562-05A	RES, CF 5% 5.6K 1		В			EA	2.00	1.00	0			08/18/94	
	R283,284 60-50563-03A	RES, CF 5% 56K 1/8		8	270		EA	5.00	1.00	0	-		00/00/00	
	R319,320,321,322,			A			EA	4.00	1.00	0			00/00/00	
_	60-50911-04A R201,202,203,204	RES MO FP 5% 2.7K		B	280				1.00	0	_		00/00/00	
	63-50272-07A R235,236,237,238 63-50471-08A	RES NO FP 5% 470 2		C	285				1.00	0	_		00/00/00	
	R329	RES MO FP 5% 4.7		В	290	-		2.00	1.00	0			00/00/00	
	63-50477-07A R267,268	RES NO FP 5% 4.7		c	295			2.00	1.00	0			00/00/00	
	63-50477-08A R269,270	RES, WW 5% .05 OH		A	145				1.00	0		÷	08/18/94	
	64-50509-08A R247,248,249,250,3	251,252	A ZW ONFREE	^	173			12.00	1.00	·	•			
2	R253,254,255,256,3 66-50100-04A R221,222,223,224	RES FUSIBLE 5% 10	OHM 1/4W	С	300	P	EA	4.00	1.00	0	0	0.00	00/00/00	99/99/99
2	R221,222,223,224 66-50100-05A R259,260,261,262,3	RES FUSIBLE 5% 10	OHM 1/2W	C	305	P	EA	8.00	1.00	0	0	0.00	00/00/00	99/99/99
	R265,266 866-50220-04A	RES FUSIBLE 5% 22	OHM 1/AU	C	310	Þ	FA	ე_∩ე	1.00	0	0	0.00	00/00/00	99/99/99
	R243,244 R66-50270-04A	RES FUSIBLE 5% 27		C	315				1.00	0			00/00/00	
	R245,246	NEG TOSTOLE JA EI	VIAT 1/71	~	J 13	r		2.00		J	J	7.30	22, 42, 44	,.,.,.

MFG,RE,210,2 Carver Corporation 14-DEC-1995 15:07

CLASS CODE: SUB-ASSEMBLIES

### BILL OF MATERIALS REPORT

PLANT CODE: CARVER

REQUESTER: ALVAREZ PAGE NO: 3

# SORTED BY ASSEMBLY PART NUMBER, COMPONENT PART NUMBER AS OF 12/14/95

SUB-ASSEMBLIES	.01												
PART: 602-00593- DESC: CCA, MAIN	- TFM-35X	UOM: EA SC	: X	REV:	: M								
				ITEM		CT.	QTY PER	YIELD	OPER	-OFFSET L	D TIME	EFFECTIV	INACTIVE
COMPONENT PART/ REFERENCE INFO	DESCRIPTION		RV		sc		ASSEMBLY	FACTR		FIXED VAR		DATE	DATE
REFERENCE INTO							2.00	1 00	0	0	n	00/00/00	00/00/00
266-50560-04D R505,506	RES FUSIBLE 5% 56		C	320		EA	2.00 4.00	1.00	0	0		00/00/00	
266-50620-04A	RES FUSIBLE 5% 62	OHM 1/4W	С	325	P	EA	4.00	1.00	Ū	•			
R209,210,211,2 320-20001-00	DIODE, 1N4148 75V	.4	C	330	P	EA	8.00	1.00	0	0	0.00	00/00/00	99/99/99
D201,202,203,20	14,205,206												
D207,208 320-20004-00	DIODE 1N4004 400V	PREP _4	В	335	P	EA	20.00	1.00	0	0	0.00	00/00/00	99/99/99
D209,210,211,2		TREI VV	_										
D216.217.218.2	19,220,221,222												
D223,224,311,3	12,513,514	u ebeen 4	В	340	D	EA	14.00	1.00	0	C	0.00	00/00/00	99/99/99
320-20006-00 D233,234,235,2	DIODE 175 WIV HIG 56.301.302.303	n SPEED .4		540	r		14100		·	•			
0304,305,306,3	)7,308,309,310									•	0.00	00/00/00	00/00/00
320-20007-00	DIODE, MR852 200V	.85	A	345	P	EA	8.00	1.00	0	0	0.00	00/00/00	77/77/77
D225,226,227,2	28												
p229,230,231,2 320-20010-03	DIODE 6AMP 400V U	NPREP	D	350	P	EA	12.00	1.00	0	0	0.00	00/00/00	99/99/99
0501,502,503,5	24,505,506,507												
0508,509,510,5	11,512	VEA 16V /	A	355	ь	EA	2.00	1.00	0	0	0.00	00/00/00	99/99/99
320-30014-00 D515,516	DIODE, ZENER 1N47	43A 104 .4	^	ررد	r	LA	2.00	1.00	·	•		-	
321-40014-01	XISTOR TO92 PNP S	M SG 2SA1015Y	A	360	P	EA	2.00	1.00	0	0	0.00	00/00/00	99/99/99
9237,238		w oo 201070		365		EA	4.00	1.00	0	0	0.00	00/00/00	99/99/99
321-40015-01	XISTOR TO92 PNP S	M SG ZSAY/U	A	303	•	EA	4.00	1.00	·	•			
9230,303,304,3 321-40016-01	XISTOR TO92 NPN S	M SG 2SC2240	A	370	P	EA	5.00	1.00	0	0	0.00	00/00/00	99/99/99
9215,216,229,3	01,302			/05	_		1.00	1.00	0	0	n nn	11/21/95	00/00/00
321-40027-01	XISTOR TO92 NPN S	M SG 25C3/92	A	405	P	EA	1.00	1.00	U	•		-	
321-60008-00	XISTOR 2006A PNP	PWR 2SA1370	A	375	P	EA	4.00	1.00	0	0	0.00	00/00/00	99/99/99
9201,202,209,2	10		_	700			4.00	1.00	0	0	0.00	00/00/00	00/00/00
321-60009-00	XISTOR 2006A NPN	PWR 2503467	A	380	۲	EA	4.00	1.00	U	•	0.00	00,00,00	,
9203,204,207,2 321-60015-01	XISTOR TO220 NPN	2SD2012	A	385	P	EA	2.00	1.00	0	0	0.00	00/00/00	99/99/99
Q451,501			_	700	_		1.00	1.00	0	0	0.00	00/00/00	00/00/00
321-60016-01 9502	XISTOR TO220 PNP	2SB1375	A	390	P	EA	1.00	1.00	•			00,00,00	,,
321-60017-01	XSTR PNP SM SG 2	A1306	В	395	P	EA	1.00	1.00	0	0	0.00	00/00/00	99/99/99
Q231			_	400			4 00	4 00	0	0	0.00	00/00/00	99/99/99
321-60018-01	XSTR NPN SM SG 2	C3298	B	400	P	EA	1.00	1.00	U	•	0.00	00,00,00	********
9232 330-30020-01	IC, SPEAKER PROTI	CT TA7317P	A	410	P	EA	1.00	1.00	0	0	0.00	00/00/00	99/99/99
IC301	•				_			4 00	^		0.00	12/04/03	99/99/99
401-10598-00	WIRE 22 AWG TR-6	BLUE 7"	-	413	P	EA	1.00	1.00	U	0	0.00	12/00/73	*******
E501 TO J107 401-20003-00	BUSS WIRE 22 GAG	SPOOL	В	415	P	FT	12.10	1.00	0	0	0.00	05/31/94	99/99/99
PREVIOUS .4",													
J4,7,9,13,14,1	8,23,24,26,31												
J32,33,34,35,3 J64,65,68,69,7													
J81,83,87,88,9													
J96,98,100,103	,104												
D451, R271,272 PREVIOUS .8" I													
	0,11,12,15,16,17												
J19,20,21,22,2	5,27,28,29,30,37												
J40,41,43-61,6 J79,82,84,85,8	3,66,67,73-76,78 6 80 90 97 99												
	06,108,109,110		•					_	_				
403-10006-00	GLUE, HOT MELT			419	E	LE	0.00	1.00	0	0	0.00	U4/1//95	99/99/99
USE UNDER C315 403-10025-01	ADHESIVE, RTV 58	13 HI TEMP	A	422	E	E/	0.00	1.00	0	0	0.00	04/15/94	99/99/99
USE UNDER C501					_								
C505,506													

NFG,RE,210,2 Carver Corporation 14-DEC-1995 15:07

BILL OF MATERIALS REPORT

PLANT CODE: CARVER

REQUESTER: ALVAREZ PAGE NO: 4


SORTED BY ASSEMBLY PART NUMBER, COMPONENT PART NUMBER
AS OF 12/14/95

CLASS CODE: 5 SUB-ASSEMBLIES PART: 602-00593-01

DESC: CCA, MAIN - TFM-35X

UOM: EA SC: X REV: M

COMPONENT PART/ REFERENCE INFO	DESCRIPTION	RV	ITEM NUMBR	sc		QTY PER ASSEMBLY	YIELD FACTR		-OFFSET LI		EFFECTIV DATE	INACTIVE DATE
501-00514-01	PCB, 200-400W HIFI AMP	A	1	В	EA	1.00	1.00	0	0	0.00	00/00/00	99/99/99
511-00019-00	HEATSINK, EXTRUDED TO-220	8	425	В	EA	1.00	1.00	0	0	0.00	00/00/00	99/99/99
H451 531-00012-01	LUG, SOLDER, #6	A	430	x	EA	1.00	1.00	0	0	0.00	00/00/00	99/99/99
EL501 550-10059-01	HARN CON .10 SPAC 3 POS 11"	A	435	В	EA	2.00	1.00	0	0	0.00	00/00/00	99/99/99
W16, 17 550-10084-03	HARN #16 TR64 RNG TRM BLK 3.25	E	421	B	EA	4.00	1.00	0	0	0.00	12/06/93	99/99/99
(SP201) 616-00093-01	CHOKE, 2.5 UH	С	440	В	EA	2.00	1.00	0	0	0.00	00/00/00	99/99/99
L201,202 617-20000-01	RELAY, SPST 24V PC MNT	C	445	P	EA	2.00	1.00	0	0	0.00	00/00/00	99/99/99



MFG,RE,210,2 Carver Corporation 14-DEC-1995 15:07

BILL OF MATERIALS REPORT

PLANT CODE: CARVER

REQUESTER: ALVAREZ PAGE NO: 1

DITT OF WATERINGS MELONI

SORTED BY ASSEMBLY PART NUMBER, COMPONENT PART NUMBER AS OF 12/14/95

CLASS CODE: 5 SUB-ASSEMBLIES PART: 602-00593-04 DESC: CCA, XSTR LEFT

UOM: EA SC: X REV: A

COMPONENT PART/ REFERENCE INFO	DESCRIPTION	RV	ITEM ST NUMBR SC UM		YIELD FACTR		-OFFSET LD FIXED VARIA		DATE
321-90001-00	XISTOR B100 NPN PMR 2SC3423-Y	A	5 P EA	1.00	1.00	0	0	0.00 00/00/00	99/99/99
9205 550-10060-01 ASW1	HRN CN 3PIN .098 SP #22TR64 3	<b>A</b>	10 B EA	1.00	1.00	0	0	0.00 00/00/00	99/99/99



MFG,RE,210,2 Carver Corporation 14-DEC-1995 15:07

BILL OF MATERIALS REPORT

PLANT CODE: CARVER

REQUESTER: ALVAREZ PAGE NO: 1

SORTED BY ASSEMBLY PART NUMBER, COMPONENT PART NUMBER

AS OF 12/14/95

CLASS CODE: 5
SUB-ASSEMBLIES
PART: 602-00593-05
DESC: CCA, XSTR RIGHT

UOM: EA SC: X REV: A

COMPONENT PART/ REFERENCE INFO	DESCRIPTION	RV	ITEM ST NUMBR SC UM	QTY PER ASSEMBLY	YIELD FACTR			LD TIME EFFECTIV INA VARIABLE DATE DATE	
321 70001 40	XISTOR B100 NPN PHR 2SC3423-Y	A	5 P E/	1.00	1.00	0	0	0.00 00/00/00 99/	<del>29</del> /99
9206 550-10060-01 A6W1	HRN CN 3PIN .098 SP #22TR64 3	A	10 B E/	1.00	1.00	0	0	0.00 00/00/00 99/	<del>29/99</del>

MFG,RE,210,2 Carver Corporation 14-DEC-1995 15:07

### BILL OF MATERIALS REPORT

#### PLANT CODE: CARVER

REQUESTER: ALVAREZ PAGE NO: 1

SORTED BY ASSEMBLY PART NUMBER, COMPONENT PART NUMBER AS OF 12/14/95

CLASS CODE: 5 SUB-ASSEMBLIES PART: 602-00600-01

DESC: CCA. INPUT - TFM-35X

UOM: EA SC: X REV: D

DESC: CCA, INPUT -	15M-35X DOM: EX SC	. ^	RCT.	•							
COMPONENT PART/ REFERENCE INFO	DESCRIPTION	RV	ITEM NUMBR S		T QTY PER H ASSEMBLY	YIELD FACTR			T LD TIME VARIABLE	EFFECTIV DATE	INACTIVE DATE
109-10022-02	PHONO JACK 2P SLDR DIP PIN GLD	В	5 P	) E	A 1.00	1.00	0	0	0.00	00/00/00	99/99/99
J100 201-00002-00	CAP CER DISC 10 PF 1000V 10%	C	10 P	E	A 2.00	1.00	0	0	0.00	00/00/00	99/99/99
c105,106 201-00013-00	CAP CER DISC 120 PF 1000V 10%	В	15 P	E	A 2.00	1.00	0	0	0.00	00/00/00	99/99/99
C103,104 201-00127-02	CAP CR DSK .01UF 50V +80-20 .2	В	20 P	) E	A 4.00	1.00	0	0	0.00	00/00/00	99/99/99
C155, 156, 157, 158 204-00101-00	CAP PLYFLM .47 UF 50V 20% RAD	A	25 P	) E	A 2.00	1.00	0	0	0.00	00/00/00	99/99/99
C101,102 204-00134-00	CAP MTL FLM .01 UF 50V 5%	A	30 F	) E	A 2.00	1.00	0	0		00/00/00	-
C107,108 204-00146-00	CAP MTL FLM .1 UF 50V 5%	В	35 F	) E	A 3.00	1.00	0	0	0.00	00/00/00	99/99/99
C153,160,161 205-00179-02	CAP LYTIC 220 UF 10V MINI 20%	A	40 F	) E	A 2.00	1.00	0	0	0.00	00/00/00	99/99/99
C109,110 260-50104-04D	RES, CF 5% 100K 1/4W .5	A	45 F	) E	A 4.00	1.00	0	0	0.00	00/00/00	99/99/99
R103,104,111,112 260-50105-04D	RES, CF 5% 1M 1/4W .5	A	50 F	) E	A 1.00	1.00	0	0		00/00/00	
R110 260-50162-04D	RES, CF 5% 1.6K 1/4W .5	A	55 F	> E	A 4.00	1.00	0	0	0.00	00/00/00	99/99/99
R117,118,119,120 260-50202-040 R101,102,129,130,	RES, CF 5% 2K 1/4W .5	A	60 F	) E	A 6.00	1.00	0	0		00/00/00	
260-50204-04D R168	RES, CF 5% 200K 1/4W -5	A	65 F	9 8	A 1.00	1.00	0	0	0.00	00/00/00	99/99/99
260-50471-04D R105,106	RES, CF 5% 470 OHM 1/4W .5	A	70 F	PE	A 2.00	1.00	0	0		00/00/00	
260-50472-04D R125,126,127,128,	RES, CF 5% 4.7K 1/4W .5	A	75 F	PE	A 5.00	1.00	0	0		00/00/00	
260-50822-04D R121,122,123,124	RES, CF 5% 8.2K 1/4W .5	A	80 F	PE	A 4.00	1.00	0	0		00/00/00	
262-31003-04D R113,114,165	RES, MF 1% 100K 1/4W .5	A	85 F	PE	A 3.00		O	0	0.00	00/00/00	99/99/99
262-33741-04D R115,116	RES, MF 1% 3.74K 1/4W .5	A	<del>9</del> 0 I	PE	A 2.00	1.00	0	0		-	99/99/99
318-40011-01 \$100	SWITCH, SLIDE 2-POS 2-POLE	A	95 1	PE			0	0			99/99/99
321-40014-01 Q151	XISTOR TO92 PNP SM SG 2SA1015Y	A	100 (	PE	A 1.00		0	0			99/99/99
321-40015-01 9105,106	XISTOR TO92 PNP SM SG 2SA970	A	105 i	PE	A 2.00	1.00	0	0			99/99/99
321-40016-01 9103,104	XISTOR TO92 NPN SM SG 2SC2240	A	110	PE	A 2.00	1.00	0	0			99/99/99
321-40027-01	XISTOR TO92 NPN SM SG 2SC3792	A	115	P	A 1.00	1.00	0	0			99/99/99
330-30021-01 U101	IC, DUAL OP AMP SIP NJM4565	B	120 1			1.00	0				99/99/99
401-20003-00 PREVIOUS .5" INSU	BUSS WIRE 22 GAGE SPOOL L, QTY 4:	B	125	P I	T 0.40	1.00		0	0.00	10/17/94	99/99/99
W5,6,7,8 501-00600-01	PCB, INPUT	C	1 1	В	A 1.00	1.00	0	0	0.00	00/00/00	99/99/99
550-00040-01 W2 (J102)	CBL ASSY-#22 6PIN TO 3PIN 6"	A	130	B	A 1.00	1.00	0	0	0.00	00/00/00	99/99/99
550-00041-01 W1 (J101)	CBL ASSY, #22 6PIN TO 4PIN 6M	A	135 1	B 1	A 1.00	1.00		0	0.00	00/00/00	99/99/99
550-00042-01 WITH E1	CBL ASSY,#18 RING LUG NO.4 7m	A	137	В	A 1.00	1.00		0	0.00	09/15/94	99/99/99
550-10056-01 W3 (J103)	HARN CON 3 PIN #22 TR64 9**	A	140	B 1	A 1.00	1.00		0	0.00	00/00/00	99/99/99

